A Database Publication

ATARI USER

Vol. 3 Vol. 8 December 1987 £1.25

RIGHT ON TARGET?

The latest launch from Atari is put to the test

[illegible]

GAME: Face the challenge of the Christmas maze

DIY: Liven your party with Atari-controlled disco lights

ACTION · EXCITEMENT · DESTRUCTION
IT IS THE WAY OF THE

JACKAL™

© KONAMI 1986

KONAMI

COMMODORE DISC £14·95
COMMODORE CASSETTE £8·95
SPECTRUM CASSETTE £7·95
AMSTRAD DISC £14·95
AMSTRAD CASSETTE £8·95
ATARI DISC £14·95
ATARI CASSETTE £9·95

KONAMI

Another gripping Arcade Conversion

DISTRIBUTED BY: N.M.C. LTD., 2 IFFLEY ROAD, LONDON W6 0PA. TEL: 01-846 9701

For subscription details please send a S A E to
KONAMI SOFTWARE CLUB
Bank Building, Bank Street, Newton Abbot Devon TQ12 2JL

KONAMI HELPLINE
0626 56789

Contents

Vol 3 No 8 December 1987

Managing Editor
Derek Meakin

Group Editor
Alan McLachlan

Features Editor
Peter Davidson

Production Editor
Peter Glover

Editorial Assistant
Neil Fawcett

News Editor
Mike Cowley

Technical Editor
Andre Willey

Advertisement Manager
Tony Nowell

Advertising Sales
John Snowden
Nora Lawton

Editorial 061-456 8383
Administration 061-456 8283
Advertising 061-456 8500
Subscriptions 061-480 0171
Telecom Gold 72:MAG001
Telex 265871 MONREF G
Quoting Ref. 72:MAG001
Prestel Mailbox 614568383

Published by
Database Publications Ltd
Europa House, 68 Chester Road
Hazel Grove, Stockport SK7 5NY

ABC 32,073 January-June 1986

Subscription rates for
12 issues, post free

£15 UK
£18 Europe (incl. Eire)
£33 Overseas (Airmail)

ISSN 0266-545X

Atari User welcomes program listings and articles for publication. Material should be typed or computer printed, and preferably double spaced. Program listings should be accompanied by cassette tape or disc. Please enclose stamped, self-addressed envelope, otherwise the return of material cannot be guaranteed. Contributions accepted for publication by Database Publications Ltd will be on an all-rights basis.

News trade distribution: Europress Sales and Distribution Limited, Unit 1, Burgess Road, Ivyhouse Lane, Hastings, East Sussex TN35 4NR. Tel: 0424 430422

A BRITISH BROADCASTING CORPORATION MICROCOMPUTER

It operates at 4 million instructions per second.

It's the world's fastest microcomputer.

It has been voted the 1987 microcomputer of the year.†

At an operating speed of 4 million instructions per second just about everything you do happens instantly. With this kind of power at your fingertips the advantages are enormous.

† Already Archimedes* has won the British Microcomputer of the Year award, a clear winner against the other two finalists, the Amstrad 1512* and the Amiga 500*.

In addition to BBC Basic V, high level languages such as C and Pascal can be used for specialist applications fully exploiting the computer's outstanding power, graphics and speed.

The huge potential of Archimedes doesn't stop there. The 310M with its built-in PC emulator can run Lotus 1-2-3*, DBASE III*, MS WORD* and other popular business programs available under MS-DOS*.

With prices starting at £749 ex. VAT for the 305 with mono monitor and rising to £1035 ex. VAT for the 310M with colour monitor the Archimedes 300 series presents unparalleled value for a computer system of such capability.

PRIORITY REQUEST

Please send me an information pack on Archimedes together with a list of dealers.

Name__________

Address__________

Postcode__________

Tel__________

☐ Tick here for written details of the 0% finance deal available through participating dealers.

Acorn Computers Ltd.,
FREEPOST 4335 BS1 3YX

Acorn
The choice of experience

OR PHONE 0800 700100

0% (APR 0%) FINANCE FOR LIMITED PERIOD

[illegible]

*MS-DOS and MS WORD are trademarks of Microsoft [illegible]
*Amiga [illegible] Machines [illegible]

£1.3 million deal brings big Email expansion

A MASSIVE expansion of MicroLink Britain s fastest-growing electronic mail service, is now being planned following the completion of a £1 3 million contract with Telecom Gold

MicroLink – which has a section specifically for Atari users – was launched in April 1985 as a means of encouraging people to start exploring the exciting new world of electronic communications

It became an instant success – and not only in Britain Computer users in Europe the Middle East and Australasia call the MicroLink service, which is housed on a Prime 750 computer in Telecom Gold s top security London head

As part of the new deal the service is being transferred to a machine that is four times more powerful – the Prime 9955

The phenomenal development of MicroLink has meant that we have now outgrown the computer that has served us so well in the last two and half years' said MicroLink chairman Derek Meakin

The new machine will give us much greater flexibility It will allow us to provide a much faster service introduce a variable charging structure to meet the different needs of our users and make possible the installation of many new and exciting facilities"



Pictured after signing the £1 3 million deal are Telecom Gold general manager Clem Jones (seated left) and head of MicroLink Derek Meakin Looking on, from left, are MicroLink sales and marketing manager Mike Heyes, Telecom Gold sales and marketing head Philip Madden, MicroLink joint managing director Michael Meakin MicroLink marketing director Peter Brameld Telecom Gold northern sales manager David Bromley and MicroLink systems manager Tim Clarkson

Atari in top gear at Motor Fair

ATARI UK caused a big stir at the MotorFair in Olympia by setting up a computer games stand

Centrepiece of the stand which embarrassed show organisers admitted was the best visited in the whole exhibition, was a line of racing cars inside which youngsters could play Pole Position

An Atari spokesman said 'We believe that many of the 300,000 people who go to the show are fathers with children under 10 We saw this as a perfect opportunity to introduce our games system to these youngsters many of whom might never have seen them before

"The organisers said we had one of the most exciting exhibits It became virtually an entertainment area for the youngsters

"We believe the introduction of the new games machine this Christmas has opened up a new market place to us The youngsters of that market place certainly responded enthusiastically at this show', said the spokesman

Parallel interface for Ataris

A LEADING supplier is aiming to make Atari 8 bit users fall in love with its new internal add on

The Computer House Universal Parallel Interface Device or Cupid will cost £39 95 and could open up the 8 bit machine to the world

A series of handlers will be produced by Computer House (01 731 1276) to enable the interface to work with modems printers and Midi using a standard 25-way D socket With a rom support system, the interface will be fully programmable

Cupid is just one of a number of products on the cards as Computer House steps up its support for the 8 bit range

A Help menu will be on offer which allows the user to put all the instructions about a program in a form which can be pulled up by a single keystroke

CH boss John May said the company was importing a growing selection of software from the US

A 130XE high resolution designer is on the cards which will work very well with CH s Snapshot

Also to be released is Word Magic which John May describes as a word processor with built in graphics It will cost £17 99

Software developers rapped

ATARI 8 bit micro users are being given a raw deal by some software developers according to Essex based retailer Clive Pulman

His firm Trybridge has sold computer software for more than four years and Pulman says he has had particular difficulty getting a regular supply of new titles for Atari 8 bit machines

'The amount of new programs coming available is pathetic said Pulman 'The machines have so much potential it is a pity that software houses are not picking up on them the way they should

Pulman says that although Americans have about 2,000 Atari 8 bit programs to choose from Britain is limited to 'a few hundred – of which many are re issues of old titles that don t fully utilise the machines' capabilities

One major software house was quick to deny the situation is as grim as Pulman describes it US Gold marketing and product manager Richard Tidsall told *Atari User* "Currently we have 65 games available on licence from America which isn t bad for just one publisher

'American buyers may have a greater choice, but what is suitable for them may not be suitable for us"

But there is good news for users – Atari UK is back in the software market itself with Twilight Zone and has another 20 rom cartridge games due for release

SOFTWARE EXPRESS Ltd.

NEW RELEASES!!!

ALTERNATE REALITY (THE DUNGEON)	DISK	£19.99
GUILD OF THIEVES	DISK	£19.95
KNIGHT ORC	CASS	£14.95
KNIGHT ORC	DISK	£14.95
DRUID	CASS	£7.95
DRUID	DISK	£12.95
THE LIVING DAYLIGHTS	CASS	£9.95
THE LIVING DAYLIGHTS	DISK	£14.95
ARKANOID	CASS	£8.95
ARKANOID	DISK	£14.95
DARG	CASS	£3.95
DARG	DISK	£7.99
JOE & THE NUCLEAR CAVERNS	CASS	£3.99
JOE & THE NUCLEAR CAVERNS	DISK	£7.99

SPECIAL OFFERS!!!

CONVERSATIONAL FRENCH	CASS
CONVERSATIONAL GERMAN	CASS
KINGS SIZE (50 GAMES)	CASS
FIRST STEPS WITH THE MR MEN	CASS
MICKEY IN THE GREAT OUTDOORS	DISK
MOUNTAIN KING	CART
MINER 2049ER	CART
BASIC (400/800)	CART
ROSENS BRIGADE	CASS & DISK
CLOWNS AND BALLOONS	CASS & DISK
SEA BANDITS	CASS & DISK
POOYAN	CASS & DISK

ONLY £5.00 EACH !!!

POLE POSITION	CASS
LONE RAIDER	CASS

ONLY £2.00 EACH !!!

TRIVIAL PURSUIT
THE ULTIMATE COMPUTER BOARD GAME FOR THE ATARI C/D £14.95/£19.99

XLENT SOFTWARE *10-PRINT-*
ALLOWS YOU TO PRINT, EDIT FONTS AND DUMP GRAPHIC 8 SCREENS TO A 1029 PRINTER.....(DISK) £14.95

THE FIRST XLENT WORD PROCESSOR
"ANTIC" MAGAZINE AWARD WINNER FOR 1987 ... (DISK) £29.95



THE
ONE
STOP
ATARI
SHOP

021 328 3585
021 643 9100

MAGAZINES - BACK ISSUES STILL AVAILABLE - PHONE FOR DETAILS

ATARI 130XE COMPUTER/XC12 DATA RECORDER PACK
INCLUDING JOYSTICK AND 6 PROGRAMES' £139.99

MINI-OFFICE II	£19.95
SYNCALC (DISK) - ADVANCED SPREADSHEET	£49.95
SYNFILE (DISK) - ULTIMATE FILING SYSTEM	£49.95

O.S.S PRODUCTS

THE WRITERS TOOL (ROM)	£69.00
BASIC XL (ROM)	£59.00
BASIC XE (ROM)	£79.00
MAC/65 (ROM)	£69.00
BASIC XL TOOLKIT	£29.95

ATARI
ST'S
AVAILABLE
FROM
£259.00
PHONE

This Advert was typeset on an Atari ST using Fleet Street Publisher and output to a Qume PS800+ Laser Printer

ATARI 400/800 OWNERS "THE PROGRAMMER "
CONTAINING BASIC ROM & MANUALS
ONLY .... £7.95!

SEND OR PHONE FOR OUR LATEST PRICE LIST
ATARI VCS /XL/XE 520/1040 (PLEASE SPECIFY)

BOOKS

DE RE ATARI A GUIDE TO EFFECTIVE PROGRAMMING	£17.99
ATARI TECHNICAL REFERENCE NOTES	£17.00
ATARI 130XE HANDBOOK (XL/XE BASIC MANUAL)	£8.95

OTHER BOOKS AVAILABLE PHONE WITH REQUIREMENTS

ATARI CARTRIDGES

ASSEMBLER EDITOR	£19.95
CAVERNS OF MARS	£7.95
DEFENDER	£7.95
DIG DUG	£7.95
DONKEY KONG JNR	£7.95
JOUST	£7.95
LOGO	£29.95
MICROSOFT BASIC II	£19.95
MISSILE COMMAND	£7.95
MUSIC COMPOSER	£7.95
SKY WRITER	£7.95
STAR RAIDERS	£7.95
TENNIS	£7.95
TYPO ATTACK	£7.95

DEALER and OVERSEAS Enquiries Welcome

514-516 Alum Rock Road, Alum Rock, Birmingham. Telephone: 021 328 3585
212-213 Broad Street, Birmingham. Telephone: 021 643 9100



Be a back seat driver

BACK seat driving takes on a new dimension in Speed Run, one of a series of Christmas releases from Red Rat

Unlike most racing games the player's point of view is behind an animated driver who turns corners and changes gear on command

Red Rat (061 835 1055) says it is the most ambitious motor driving game ever written for an 8 bit machine

The object is to complete the various stages of a motor rally in a Ford Sierra RS Cosworth with its five-speed gearbox

The company also has two double packs ready for release

In the first, Planet Attack is paired with Mad Jax The former is a multi speed 3D scrolling shoot em up in which the player must guide a craft on a mission to destroy a series of outposts guarded by vicious aliens

Mad Jax gives a bird's eye view of an armoured tank which must negotiate a desert road and a city, taking on all opponents along the way

The second double pack features platform adventures Burglar Bill and Pot hole Panic

All Red Rat pre Christmas releases are being sold at £7 95 on cassette and £9 95 on disc

Colour-coded discs

A RANGE of 5 25in coloured discs for Atari computers has been announced by Center-

The discs which come in five colours have been produced as a result of customer demand for an easier way to identify their date discs from program or back up discs

John Taylor, managing director of Centec (0689 35353) told Atari User 'Single colour discs have been causing problems for our customers Now that they have a choice of colours it is possible for them to store data on red discs back up discs on green and program discs on blue

'With the addition of yellow and black it gives the customer greater flexibility in storage identification'

DTP PACKAGE

A £20 desktop publishing package for Atari 8 bit machines is scheduled for release in the new year

US software house XLent – now half owned by Software Express (021 328 3585) – has put together on disc Typesetter and Rubber Stamp

Typesetter helps with page layout, while Rubber Stamp is essentially a font designer

THE GALLUP CHART TOP 20

ATARI SOFTWARE

THIS MONTH	LAST MONTH	TITLE (Software House)	PRICE
1	◁ 1	**DECATHLON** *Firebird*	1.99
2	△ 6	**FEUD** *Mastertronic*	1.99
3	▽ 2	**180** *Mastertronic*	2.99
4	△ 10	**DIZZY DICE** *Players*	1.99
5	△ 8	**GAUNTLET** *US Gold*	9.95
6	●	**MONKEY MAGIC** *Alternative*	1.99
7	▽ 3	**MILK RACE** *Mastertronic*	2.99
8	▽ 5	**ON CUE** *Mastertronic*	2.99
9	●	**HOVVER BOVVER** *Mastertronic*	1.99
10	△ 16	**LEADERBOARD** *US Gold*	9.95
11	▽ 4	**STORM** *Bulldog*	1.99
12	▽ 9	**SILENT SERVICE** *Microprose/US Gold*	9.95
13	●	**DRUID** *Firebird*	9.95
14	●	**RED MAX** *Code Masters*	1.99
15	▽ 14	**BOULDER DASH II** *First Star/Prism*	2.99
16	●	**INVASION** *Mastertronic*	1.99
17	●	**FOUR GREAT GAMES** *Micro Value*	3.99
18	●	**FOOTBALL MANAGER** *Addictive*	1.99
19	▽ 7	**LIVING DAYLIGHTS** *Domark*	9.95
20	●	**FOUR GREAT GAMES 2** *Micro Value*	3.99

Compiled by Gallup/Microscope

Decathlon retains the first position for another month but there are eight new and re entries in the chart The highest entry is the new Monkey Magic from Alternative Watch out for Micro Value's two compilations which also enter the chart in time for Christmas

Lost in your listings?

Colour your cursor with this superb utility from David Steele

HOW many times have you been editing a program on screen, then looked away for a minute, looked back and couldn't find the cursor? Well here's a program that tracks the normal cursor with a coloured player missile

It will help you find it in a screen full of text or you could even use the cursor to indicate an INPUT from the keyboard by changing its colour after each entry

The new cursor shows up particularly well in reverse video strings, where it is often easily lost during editing. It's visible on any Graphics 0 screen in Basic, Dos or Assembler, and will also appear in the text window. It will remain even if you press Break or System Reset

There are two versions of the program. Program I creates an AUTORUN SYS file on any Dos disc while Program II creates an AUTOBOOT cassette. Type in the program you need and use the Get it Right III checksum to correct any typing errors

If you use disc save your program as a master, then Run it. It will proceed to create a SYS file to disc which will boot into memory on power-up

Tape users should save a copy of the program as a master, put a cassette in the recorder, rewind it and press Record and Play together. Run the program and, when you hear two beeps, press Return to save your autoboot version to tape. When the program ends, switch the computer off and rewind the cassette

Getting the coloured cursor is now just like booting a game. Press Play, hold down Start and switch on. When you hear the beep press Return and after about 15 seconds the coloured cursor will appear. Remember to stop the cassette

The cursor colour is initially set to orange/red but you can alter this in either program by changing the 240 – line 1050 of Program I, line 1040 of Program II – to any number from 1 to 255. Some of the colours available are given in the panel below. If you want to change the cursor colour once the program is loaded it is controlled by poking 705 with an even number from 0 to 254. For even better effects, try altering the text colours by poking 709 and 710

POKE	COLOUR
710 1	Black
710 54	Pink
710 64	Purple
710,94	White
710,164	Green
710 242	Red/Brown

Pokes to give different colour to the cursor

If you wish to use player missile graphics in your program, switch off the coloured cursor and when you have finished with them enter POKE 54279 4 POKE 53277 3 before switching them back on

The coloured cursor boots from disc or cassette into page 6 and the program itself occupies the lower half of this area of memory. The upper half is used as player 1 in double line resolution mode. For machine code enthusiasts, Program III is the assembler source listing of the disc version. Program IV shows the changes necessary for cassette booting

The program is protected against the Reset button and the Break key, meaning that once installed the only way to totally disable it is to turn the power off. If at any time you lose the colour of the cursor press Reset to bring it back

The cursor can be affected be poking directly into the code that controls it. Some useful ones are given in panel above

Listing I: Program to create AUTORUN.SYS disc file.

```
10 REM COLOURED CURSOR
11 REM BY GLOBAL COMPUTER SERVICES
12 REM (c)ATARI USER
13 REM DISC AUTOBOOT
20 GRAPHICS 0:POSITION 9,11
30 ? "Setting up AUTORUN.SYS"
40 OPEN #1,8,0,"D:AUTORUN.SYS"
50 RESTORE 1000
60 READ D:IF D<0 THEN 80
70 PUT #1,D:GOTO 60
80 CLOSE #1
90 POSITION 15,13:? "ALL DONE":END
100 REM -------------------------
1000 DATA 255,255,0,6,127,6,165
1010 DATA 12,141,22,6,165,13,141
1020 DATA 23,6,169,21,133,12,169
1030 DATA 6,133,13,76,24,6,32
1040 DATA 0,0,169,4,141,7,212
1050 DATA 169,3,141,29,208,169,240
1060 DATA 141,193,2,173,36,2,141
1070 DATA 126,6,173,37,2,141,127
1080 DATA 6,169,7,162,6,160,80
1090 DATA 76,92,228,216,169,0,168
1100 DATA 153,128,6,200,16,250,173
1110 DATA 240,2,208,50,169,46,141
1120 DATA 47,2,189,4,205,191,2
1130 DATA 240,6,166,87,208,34,240
1140 DATA 6,169,24,166,123,240,26
1150 DATA 24,101,84,10,10,168,162
1160 DATA 3,169,60,153,131,6,136
1170 DATA 202,16,249,165,85,10,10
1180 DATA 105,46,141,1,208,76,0
1190 DATA 0,224,2,225,2,0,6,-1
2000 REM -------------------------
2010 REM The 240 in line 1050 is
2020 REM the initial cursor colour
```

```
10 CP1 (X)     100 CUS (1)   1110 GJ5 (
11 CY1 (D)    1000 EE8 (L)   1120 J/C (T
12 CX1 (X)    1010 EY3 (S)   1130 HJ (
13 P21 (D)    1020 FDN (M)   1140 PA (S
20 RUK (6)    1030 F8A (3)   1150 GJA (
30 DDG (4)    1040 DPA (Y)   1160 FEW (
40 RF7 (2)    1050 P1Y (2)   1170 FK? (
50 TCW (H)    1060 FJH (V)   1180 SW2 (W)
60 FWK (N)    1070 GW5 (5)   1190 ENO (A)
70 4AM (F)    1080 FWK (6)   2000 CXP (6)
80 LV6 (A)    1090 MY3 (K)   2010 DOP (4)
90 8H1 (G)    1100 N2H (O)   2020 D2P (G)
```

POKE	ACTION
752,1	Cursor off
752,0	Cursor on
53277,0	Remove colour
53277,3	Restore colour

Pokes that affect the cursor

Listing I1 Program to create AUTOBOOT cassette file

```
10 REM COLOURED CURSOR
11 REM BY GLOBAL COMPUTER SERVICES
12 REM (c)ATARI USER
13 REM CASSETTE AUTOBOOT
20 GRAPHICS 0:POSITION 9,11
30 ? "Setting up CASSETTE BOOT"
40 OPEN #1,8,128,"C"
50 RESTORE 1000
60 READ D:IF D<0 THEN 80
70 PUT #1,D:GOTO 60
80 CLOSE #1
90 POSITION 15,13:? " ALL DONE ":END
100 REM ----  ----  -   -    -----
1000 DATA 0
1010 DATA 1,0,6,13,6,169,60
1020 DATA 141,2,211,24,96,169,4
1030 DATA 141,7,212,169,3,141,29
1040 DATA 208,169,240,141,193,2,173
1050 DATA 36,2,141,113,6,173,37
1060 DATA 2,141,114,6,169,7,162
1070 DATA 6,160,49,76,92,228,216
1080 DATA 169,0,168,133,128,6,208
1090 DATA 16,230,173,240,2,208,50
1100 DATA 169,46,141,47,2,169,4
1110 DATA 205,191,2,240,8,156,87
1120 DATA 208,36,240,6,169,24,166
1130 DATA 125,240,26,24,101,84,10
1140 DATA 10,168,162,3,169,10,153
1150 DATA 131,6,136,202,16,249,165
1160 DATA 85,10,10,103,46,141,1
1170 DATA 208,76, 1
2000 REM --------- -------- -------
2010 REM The 240 in line 1040 is
2020 REM the initial cursor colour
```

Get it right! II

10 CP1 (Y)	100 CUS (P)	
11 CT1 (Q)	1000 L1X (S)	
12 CX1 (X)	1010 CYW (F)	1110 SNJ (P)
13 D21 (Q)	1020 F2R (K)	1120 GUV (1)
20 BUK (6)	1030 F5E (C)	1130 F7S (J)
30 4HX (2)	1040 R25 (P)	1140 GVU (3)
40 5J3 (N)	1050 GO8 (V)	1150 PGH (G)
50 TCW (7)	1060 FJ8 (3)	1160 FCS (D)
60 FWK (2)	1070 HDX (E)	1170 YHR (H)
70 4AM (S)	1080 HMV (6)	2000 CXP (N)
80 LV5 (W)	1090 GF4 (T)	2010 DOP (H)
90 BH1 (R)	1100 FJV (N)	2020 D2P (N)

PROGRAM BREAKOOWN

20 50	Set up screen and open file
60 70	Copy program data to file
80-90	Close file report all done

MACHINE COOE

470-690	Install coloured cursor into the disc or cassette init vector This protects against Reset
730-930	Define the player missile area and turn it on The cursor colour is set here but it can be changed at any time The position of the player is set during Vblank, so that routine is installed
970-1060	Erase the cursor from its current position
1080 1090	Check whether the coloured cursor is required
1110-1120	Force the player missile to appear, and also set double resolution mode This is done in every Vblank because a change of graphics mode will alter SDMCTL without warning
1170 1300	Test to see if a GR 0 screen, GR 0 text window or if no GR 0 screen showing at all Also decide the vertical position of the player-missile
1360-1560	Draw the cursor into the player, and position it horizontally The final exit is to any other Vblank code that may have been installed

Listing II MAC65 Source code

```
10 ,LIST#D SOURCE LISTING
20 ,
30 ,  Coloured cursor for XL/XE
40 ,       DISK VERSION
50 ,
60 ,  By David Steele
70 ,  (c)ATARI USER
80
90 ,
0100 , This program will create an
0110 , AUTORUN SYS file on a Dos
0120   format disc
0130 ,
0140 ,
0150 ,
0160      OPT NO LIST
0170 ,
0180 , BEGIN
0190
0200 , <This is a MAC65 source file>
0210 ,
0220 DOSINI = $0C
0230 ROWCRS = $54
0240 COLCRS = $55
0250 RINDEX   $57
0260 SWPFLG = $7B
0270 ,
0280 VVBLKD   $0224
0290 SDMCTL = $022F
0300 HOTSCR   $026F
0310 PCOLR1 = $02C1
0320 RUNADR = $02E0
0330 CRSINH   $02F0
0340 ,
0350 HPOSP1 = $D001
0360 GRACTL = $D01D
0370 PMBASE   $D407
0380 ,
0390 SETVBV = $E45C
0400 ,
0410 ,------------            -------
0420 ,
0430 PLAYER = $0680
0440 ,
0450     *   $0600
0460 ,
0470 ,Program runs here when loaded
0480 ,
0490 START
0500 ,
0510 ,Intercept DOS init vector to
0520 ,re-enable cursor after Reset
```

Turn to Page 10 ►

◄ From Page 9

```
0530 ,
0540      LDA DOSINI+0
0550      STA RESET+1
0560      LDA DOSINI+1
0570      STA RESET+2
0580 ,
0590      LDA # <RESET
0600      STA DOSINI+0
0610      LDA # >RESET
0620      STA DOSINI+1
0630 ,
0640      JMP INIT
0650 ,
0660 ,Comes here after Reset
0670 ,
0680 RESET
0690      JSR 0          ; old DOSINI
0700 ,
0710 ,---------             -    --
0720 ,
0730 INIT
0740      LDA #4
0750      STA PMBASE  ,player area  s
0760 ,                 pages 4  7
0770      LDA #3
0780      STA GRACTL   show p ayer
0790 ,
0800      LDA #$F0
0810      STA PCOLR1   cursor colour
0820 ,
0830 ,Player cursor will follow real
0840 ,cursor during deferred Vblank
0850 ,
0860      LDA VVBLKD+0 ,keep existing
0870      STA VBI OUT+1  Vblank stuff
0880      LDA VVBLKD+1
0890      STA VBI OUT+2
0900      LDA #7
0910      LDX # >VBI  ,install ours
0920      LDY #  VBI
0930      JMP SETVBV  ,RTS
0940 ,
0950 ,----- ----- ---
0960 ,
0970 VBI
0980      CLD          ,might be in
0990 ,                 , DECIMAL mode
1000      LDA #0
1010      TAY
1020 ,
1030 ERASE LOOP
1040      STA PLAYER,Y ,erase cursor
1050      INY
1060      BPL ERASE LOOP
1070
1080      LDA CRSINH  ,cursor
1090      BNE VBI OUT , inhibited ?
1100 ,
```

```
1110      LDA #$2E     ,enable players
1120      STA SDMCTL   , in single res
1130 ,
1140 ,(any GR  alters SDMCTL so it
1150 , is constantly restored here)
1160 ,
1170      LDA #4
1180      CMP BOTSCR  ,4/24
1190      BEQ WINDOW  ,text window ?
1200 ,
1210      LDX DINDEX  ,full screen but
1220      BNE VBI.OUT , not GR 0 ?
1230 ,
1240      BEQ DRAW    ,always branch
1250 ,
1260 WINDOW
1270      LDA #24
1280 ,
1290      LDX SWPFLG  ,cursor in main
1300      BEQ VBI OUT , GR  screen ?
1310 ,
1320 ,Cursor is  n
1330 ; main GR 0 screen (A- 4)
1340 ; text window      (A-24)
1350 ;
1360 DRAW
1370      CLC
1380      ADC ROWCRS
1390      ASL A
1400      ASL A
1410      TAY          ,vertical pos
1420 ,
1430      LDX #5
1440      LDA #$3C     cursor data
1450 ,
1460 DRAW LOOP
1470      STA PLAYER+3,Y
1480      DEY
1490      DEX
1500      BPL DRAW LOOP
1510 ,
1520      LDA COLCRS
1530      ASL A
1540      ASL A        ,(CLC)
1550      ADC #46
1560      STA HPOSP1   ,horizontal pos
1570 ,
1580 VBI OUT
1590      JMP 0        ,exit to other
1600 ,                 , Vblank stuff
1610 ,
1620      .IF *>PLAYER
1630        .ERROR "Code hit Player
1640        ENDIF
1650 ,
1660 ,----------      ----- -------
1670 ,
1680      *=  RUNADR
1690 ,
1700       WORD START
1710 ,
1720 , END
```

Listing IV Modifications to listing III to create a cassette AUTOBOOT file

```
10 ,LIST#D PROGRAM3 LST
20 ;
30 ,  Coloured cursor for XL/XE
40 ,      CASSETTE VERSION
50 ,
51 ,*THESE PROGRAM LINES REPLACE THE*
52 ,*CORRESPONDING LINES IN PROGRAM2*
53 ,
0320 PACTL   $D302
0410 ;-- ----------------- --      --
0420 ,
0430 PLAYER = $0600
0440 ,
0450     *=  $0500
0460 ,
0470 LOAD
0480 ,
0490  Header data for cassette boot
0500
0510      .BYTE 0      ,unused
0520       BYTE 1      ,# records
0530       WORD LOAD  ,load addr
0540       WORD INIT  ,init addr
0550 ,
0560 ,Boot continuation
0570 ,
0580      LDA #$3C    ,stop motor
0590      STA PACTL
0600      CLC          ,boot OK
0610      RTS
0620 ,
0630 ,
0640 ,
0650 ,
0660 ,
0670 ,
0680 , B S  inits here after boot
0690 ,             & on every Reset
0700 ,
0710 ,--------- --     - -------
```



COMPUTERWARE

PO BOX 318, STOKE-ON-TRENT, ST6 6UX

Brand New Software, Normally Despatched Within 24Hrs!! Up to 20% Discount on latest titles!!

TITLE	Case	Disc
180	2.70	-
221B Baker Street	-	12.50
4 Great Games	3.50	-
4 Great Games 2	8.00	
[illegible]	1.99	-
Alternate Reality 2		15.00
Alley Cat	2.70	
Arkanoid	7.50	11.00
Astromeda	1.99	
[illegible]	8.00	-
[illegible]		18.00
[illegible]	8.00	12.00
Battle of [illegible]		24.00
[illegible] Simulator	1.99	
Boulderdash 3	2.70	-
Bounty Bob Strikes Back	2.70	
Brainstorm	-	24.99
Broadsides		24.99
[illegible]	1.99	
[illegible]	1.99	
[illegible]	8.00	12.50
[illegible]	-	24.00
Chimera	1.99	-
Chicken Chase	2.70	
Colony	1.99	
Conflict in Vietnam	12.50	18.00
Colonial Conquest	-	24.00
Colossus 4 Chess	8.00	12.50
Computer Ambush		24.00
Crystal Raider	1.99	
[illegible]	3.50	7.00
Despatch Rider	1.99	
[illegible]	2.70	-
[illegible] in the Desert	12.50	-
Deeper Dungeons	4.50	8.50
Colossus 2	2.99	-
[illegible]	1.99	-
[illegible]	2.70	
Druid	8.00	12.50

TITLE	Case	Disc
[illegible]	-	24.99
[illegible]	1.99	
[illegible]	1.99	
Fight Night	8.99	12.50
Fidget	2.70	
Flight Simulator 2	-	39.95
Footballer of the Year	2.50	12.50
Football Manager	7.50	
Four Star Compilation Vol 1	8.50	8.00
Four Star Compilation Vol 2	8.50	8.00
Frenesis	1.99	
Gauntlet	8.00	12.50
Gemstone Warrior		18.00
[illegible]	3.99	
Gremlin Hits Vol 1	8.50	12.50
[illegible]	7.95	
[illegible]	1.99	
Gun Law	1.99	
Guild of Thieves	-	18.50
Hardball	8.00	12.00
Henry's House	1.99	
[illegible]	2.70	
Hover Bovver	1.99	
Hollywood Hi Jinx		24.00
[illegible]	2.70	-
International Karate	5.50	10.50
[illegible]	1.99	
Jewels of Darkness	12.50	12.50
[illegible]	3.50	7.00
Kampfgruppe		24.00
Kennedy Approach	8.00	12.50
Kikstart	1.99	
Knight Orc		12.50
Last V8	2.70	-
Leaderboard	8.00	12.00
Leaderboard Tournament	4.50	8.50
Living Daylights	8.00	12.50
Loco	1.99	
[illegible] Brigade	-	24.50
Milk Race	1.99	

TITLE	Case	Disc
Micro Rhythm	1.99	
Mutant Camels	1.99	
Master Chess	1.99	
Mercenary Compendium	12.50	15.00
Missing One Droid	2.70	
Mini Office 2		16.00
Mindwheel	-	20.00
[illegible]	2.20	
Montezuma's Revenge	8.00	12.00
[illegible]	-	20.00
[illegible]	8.00	
Molecule Man	1.99	
Music Construction Set		12.50
New York City	2.70	
Ninja	2.70	
Ninja Master	1.99	
Ogre		16.00
Olympic Skier	2.70	-
One Man & His Droid	1.99	
On Cue	2.70	
Pawn		18.00
Panik	2.70	
Phantasie 2		18.00
Philosopher's Quest		12.50
Phantom	8.50	8.00
[illegible]		8.00
[illegible]	8.99	-
[illegible]	1.99	
Preppie	2.70	
Print Shop		32.95
[illegible]	8.95	12.95
Red Max	1.99	
[illegible]	8.99	12.50
Silent Service	8.00	12.50
Silicon Dreams	12.50	12.50
Smash Hits Vol 5	8.00	12.50
Smash Hits Vol 6	8.00	12.50
Smash Hits Vol 7	8.00	12.50
Solo Flight 2	8.00	12.50
Spellbound	2.70	

TITLE	Case	Disc
Spindizzy	8.00	12.50
Spy Hunter	1.99	
Spiderman	2.70	
Stratosphere	1.99	-
[illegible]	2.70	
Steve Davis Snooker	7.50	
[illegible]	1.99	
Survivors	2.70	
Super [illegible]	8.00	
Superman	2.70	
Submarine Commander	1.99	-
[illegible]	1.99	
Tank Commander	1.99	
[illegible]	1.99	
Tomahawk	8.99	13.50
Trailblazer	8.00	12.50
Trivial Pursuit	12.50	18.50
Ultima 4	-	15.00
Universal Hero	1.99	
USAAF		25.00
Vegas Jackpot	1.99	
Vietnam	—	12.50
Warship	-	24.99
Wargame Construction Set		18.00
[illegible]	1.99	
War in Russia	-	24.00
Who Dares Wins 2	6.99	8.00
Winter Olympiad	6.50	9.00
Wizards Crown		18.50
[illegible]	1.99	
[illegible] Manager	8.00	11.50
Zaxxon	8.99	
Zork 3	-	20.00

Joysticks
Quickshot II £9.50 Quickshot II Turbo £12.50
Cheetah 125 £8.50 [illegible] £13.50
Competition Pro Extra £14.50 [illegible] £17.00
[illegible] (Model [illegible]) Only £5.99
[illegible]
[illegible] £29.95 [illegible] £2.00

All software consists of genuine, brand new, original titles. Prices include post & packing (Orders of less than £6.00 in total please add 50p) Europe add £1.00 for 1st item then 50p for each additional item. Subject to availability, all software is usually despatched within 24 Hrs. Please make Cheques/Pos payable to **COMPUTERWARE**

MILES BETTER SOFTWARE

221 Cannock Road, Chadsmoor, Cannock,
Staffs WS11 2DD Tel. (05435) 79099

US GOLD	Case	Disc
Rebel Charge		22.95
[illegible]		22.95
221B Baker Street		11.95
Broadsides		22.95
U.S.A.A.F.		26.95
Computer Ambush		25.95
Warship		25.95
Carrier Force		26.95
Colonial Conquest		22.95
Wizards Crown		18.95
Battle of Antietam		26.95
Kampfgruppe		26.95
Printshop		35.00
Graphics Disc I		17.95
Graphics Disc II		17.95
Platform Perfection	8.95	
[illegible] + Dropzone + Caverns	8.95	
Atari Aces	8.95	
Shoot 'em up	8.95	
Summer Games		10.95
Arcade Classics	7.95	
Temple of Apshai Trilogy		11.95
Ultima IV		16.95
Raid Over Moscow	7.95	11.95
Beach Head I		11.95
Leaderboard	7.95	11.95
Super Huey	8.95	11.95
Field of Fire		11.95
Vietnam		11.95
Gauntlet	8.95	11.95
Alternate Reality II		18.95
Phantasie		18.95
Gettysburg		25.95
Panzer Grenadier		22.95
War Game Construction Set		18.95
Mech Brigade	—	26.95
Leaderboard Tournament	4.99	8.95
Gauntlet Deeper Dungeon	4.99	8.95
War in Russia		25.95
ENGLISH SOFTWARE	**Case**	**Disc**
Smash Hits Vol. 5	8.95	12.95
Smash Hits Vol. 6	8.95	12.95
Smash Hits Vol. 7	8.95	12.95

Phone for availability

ACTIVISION	Case	Disc
[illegible]	8.95	
CODE MASTERS	**Case**	
BMX Simulation	1.99	
Red Max	1.99	
DOMARK	**Case**	**Disc**
Living Daylights	8.95	12.95
Trivial Pursuit	12.95	18.95
ELECTRIC DREAMS	**Case**	**Disc**
Spindizzy	8.95	12.95
DIGITAL INTEGRATION	**Case**	**Disc**
Fighter Pilot	8.95	10.95
Tomahawk	8.95	12.95
NOVAGEN	**Case**	**Disc**
Mercenary	7.95	10.95
Second City	5.95	8.95
Mercenary Comp. Pack	12.95	16.95
DATABYTE	**Case**	**Disc**
Spy V Spy II	7.50	12.00
Graphic Art Dept		19.95
Aztec	7.95	12.95
Spy V Spy I	8.95	12.95
Boulder Dash Construction Kit	8.95	12.95
IMAGINE/OCEAN	**Case**	**Disc**
[illegible]	8.95	13.95
Arkanoid	7.95	11.95
Green Beret	7.95	
INFOCOM	**Case**	**Disc**
Station Fall		22.95
Hitchhikers Guide to the Galaxy		26.95
Lurking Horror		22.95
MASTERTRONIC	**Case**	**Disc**
On Cue	2.99	
[illegible]	1.99	
180	2.99	
Amaurote	2.99	
Universal Hero	1.99	
Kik Start	1.99	
Last V8	2.99	
Ninja	2.99	
S.W.A.T.	1.99	
Molecule Man	1.99	
Crystal Raider	1.99	
Gun Law	1.99	
Mutant Camels	1.99	

	Case	Disc
Frenesis	1.99	
Hover Bovver	1.99	
RAINBIRD	**Case**	**Disc**
Jewels of Darkness	12.95	12.95
Guild of Thieves		18.95
Silicon Dreams	12.95	12.95
The Pawn		16.95
BUBBLE BUS	**Case**	**Disc**
Starquake	7.95	11.95
GREMLIN GRAPHICS	**Case**	**Disc**
Trail Blazer	7.95	11.95
Footballer of the Year	8.95	12.95
SYSTEM 3	**Case**	**Disc**
International Karate	5.95	11.95
SEGA	**Case**	**Disc**
Zaxxon + Pooyan	8.95	9.95
TYNESOFT	**Case**	**Disc**
Who Dares Wins II	8.95	8.95
Rally Speedway ROM only		8.95
Phantom	8.95	8.95
DATABASE	**Case**	**Disc**
Mini Office I		10.95
MICROPROSE	**Case**	**Disc**
Silent Service	9.95	10.95
F-15 Strike Eagle	9.95	10.95
Solo Flight II	9.95	10.95
Battalion Commander		10.95
Decision in the Desert	11.95	14.95
Conflict in Vietnam	10.95	14.95
C.D.S. SOFTWARE	**Case**	**Disc**
Brian Clough's Fortunes	12.95	15.95
Colossus Chess IV	8.95	12.95
ORIGIN	**Case**	**Disc**
Autoduel		17.95
Ogre		18.95
Ultima III	—	19.95
Ultima IV		16.95
ATARI SOFTWARE	**Case**	**Disc**
Star Raiders II		12.95
	Cartridges	
Joust		8.95
Tennis		8.95
RED RAT SOFTWARE	**Case**	**Disc**
Compilation 1	8.95	8.95
Compilation 2	8.95	8.95
Astro Droid	6.95	8.95
Space Lobster	6.95	8.95
Sprong	6.95	8.95

	Case	Disc
[illegible] Droid	5.95	8.95
Screaming Wings	5.95	8.95
SUBLOGIC		**Disc**
Flight Simulator II		39.95
San Francisco		21.95
Japan		21.95

BUDGET TITLES

	Case	Disc
Colony	1.99	
[illegible]	1.99	
Football Manager	2.99	
Master Chess	1.99	
Micro Rhythm	1.99	

HARDWARE

Sega System £88.00
Nintendo System £88.00
Atari 520ST FM £299
Epson LX800 £249.00
Ferguson CM805 Monitor/TV £299.00
XC12 cassette unit + games [illegible] £34.00
65XE Computer incl. software & joystick £79.00
65XE Computer incl. joystick & lightgun £119.95
130XE Computer pack incl. Computer XC12 software & joystick £135.00
XF 551 D/S Disc Drive £175.00
XMM 801 Printer £180.00
CX77 Touch Tablet £48.00

PHONE FOR LATEST ST PRICES

For full list of ST Software see our advert in the Atari ST User

All prices are correct at time of going to press. [illegible]
Please add £1 per item for overseas orders
Please make Cheques or Postal Orders payable to: MILES BETTER SOFTWARE
Phone or write for comprehensive stock list for Atari and ST [illegible] + hardware

WHILE STOCKS LAST

TRADE ENQUIRIES WELCOME
PHONE FOR DETAILS

Graphics galore

Program Blazing Paddles
Price £26 95
Supplier Baudville/ABC
Holdings 53 Cambridge
Street Aylesbury Bucking
hamshire HP20 1RP
Tel 0296 27166

OVER the last year there has been an increase in the amount of budget software available for the Atari micros

The popularity of these programs seems to have overshadowed the full capabilities of the micro so it was with interest that I viewed Blazing Paddles

This graphics package offers you more than 250 colours a range of pre drawn shapes stored on disc, three variations of text four different input drawing devices and an icon driven menu of commands

You load the program with Basic switched off and the first thing to appear is the Drawing Device menu This is where you choose your drawing tool – joystick paddles, touch tablet or trackball

I found the joystick easiest to use as the scrolling and medium pace takes you around the screen comfortably if a little jerkily

The Touch Tablet requires a Koala Pad – I tried to use my Atari Touch Tablet but as I moved the stylus up the crosshair cursor moved down As a result I stuck with the joystick option

Moving on to the drawing mode the menu icons are placed across the screen at the top and bottom This effectively leaves you only half a screen for your drawing

Blazing Paddles has the usual range of drawing commands – Clear screen Text Lines Ovals Solid box Outline box Dots Spray can Fill and Zoom Attached to these are the pre drawn shapes and window features

The majority of commands are selected by placing the screen crosshair cursor on top of an icon and pressing the fire button Some of the commands speak for themselves but others will benefit from a brief explanation

Window is a visual cut and paste routine By dragging a dotted outline around a portion of the drawing you want to cut you can send it to a buffer

This allows you to move a chosen segment around the screen by simply picking the spot and hitting the fire button

Text can be selected in three sizes and each is double the height of the last with the smallest similar to the standard Atari character set

There are two additional styles – italic and bold But only one style at a time can reside in memory

Also on disc are three files containing various pre drawn shapes When first loaded the program defaults to a set of six shapes which includes buildings and vehicles

These can be moved using the cursor flipped from side to side and rotated in 60 degree increments before placing with the fire button There is also a file of more than 30 musical symbols ready for pasting

The Colour Selection menu displays 16 colours with up to 16 variations of shade in each You choose a colour by selecting a playfield register – 0 1 2 or 3 – then you must decide on a main colour and finally on a shade This procedure is a little time consuming

If you take advantage of the six pre set pattern boxes found at the base of the colour palette screen you can also mix two colours for the patterns These are a mixture of horizontal and vertical lines in a checker board design

The Spray command produces a stippled effect using a defined colour – although there doesn't seem any method of modifying the nozzle pattern

A more useful method of drawing is provided by the seven different painting brushes, and a mixture of these can give a very nice effect to your picture

The Fill option is linked to the colour spectrum and allows you to flood an area with a colour or pattern

Zoom works by splitting the screen in two The top half is a normal representation of the picture while the bottom shows an expanded view You can then carry out



Turn to Page 14 ▶

◄ *From Page 13*

close detail work on an larged area of the picture

It s essential that an art package allows you to save your creations and this one has a reasonable Load and Save feature – which allows you to process pictures or windows shapes and character sets

There are also facilities to view a disc directory erase a file and format a data disc – all the options you need are included

Each picture is stored as a 62 sector uncompacted file which is compatible with the Micropainter art pack

The windowing feature is handy for storing any size blocks of a picture By cutting a section from your drawing and storing it in the buffer you can move directly to the disc operations and save the block to disc

This procedure also works in reverse so blocks can be cut from disc and pasted to the screen Probably one of the most useful features available is the Undo key, which will cancel your last command and revert to the original display

A Help file that can be viewed at any time is also included on the disc but only gives very brief information

There is one sample picture file and a useful Basic program with a short machine code routine to enable you to display pictures from within your own programs

Printing your picture is all part of the fun of painting programs and Blazing Paddles has drivers for Epson Gemini 10X Panasonic and Okidata



Unfortunately the 1029 dot matrix printer is not supported but as the picture file is saved in the 62 sector format you can always print it out by using the listing for the 1029 printer published in the July 87 issue of *Atari User*

Overall Blazing Paddles will be of limited use to experienced Atari users as only four colours can be displayed at any time and it doesn t have the range of commands that the Graphics Art Department [illegible] the [illegible] drawn shapes and the standard [illegible]

Blazing Paddles is a [illegible] art package Though not ideal for experienced computer artists it is a great introduction to art and superb for children of all ages

Alan Goldsbro

Devilish fun



Program Little Devil
Price £9 95 (disc) £7 95 (cassette)
Supplier Red Rat Software 11 15 Fennel Street Manchester M4 3DU
Tel 061-835 1056

THE Little Devil in question is trapped in the very bowels of Hades

Now I had always thought that such a place would be the natural sort of habitat for devils of all sizes but for some reason Old Nick s protege wants out

To escape his eternal torment in this fiery furnace he must release the scores of lost and lonely souls suffering down below Having done that he must rescue Linarta the daughter of Earl Mordred

If successful he moves in to further realms taking him nearer to the Castle Despair where the fair Linarta awaits rescue

The diminutive demon materialises at the bottom corner of the screen and by jumping and dodging must collect the souls stuck in Limbo

Out to prevent him are a collection of ghastly ghouls ghosties and gremlins which defend their domain with diabolic devotion

He has the additional problem of lack of time – strange considering he is stuck in eternity

An indication of the time elapsed is shown on the souls of the unfortunates counting down from seven to zero and he will be hard pushed to clear a screen within one lifespan

Lucifer s demons jealously guard the lost souls Some home in on him while others wander around at random or follow set paths

Also floating around s an energy pill which gives your Bouncing Beelzebub an extra life if you touch it You are able to gain extra lives a number of times on each screen

The power pill can occasionally disable the gremlins and ghosties allowing them to be destroyed for a short period of time – in much the same way as in Pac Man

The graphics are pleasantly drawn movement is smooth and game play reasonably paced The sound effects are adequate which is more that I can say about the tune

I quite enjoyed what I saw of Little Devil although I only had a pre release copy and only the first level was available for inspection

Even on that rather limited basis I am sure this game will appeal to platform addicts although bearing the music in mind perhaps with the proviso that they are tone deaf

Niels Reynolds

Sound	6
Graphics	7
Playability	7
Value for money	7
Overall	7

King-sized

Program: Knight Orc
Price: £14.95 (cassette and disc)
Supplier: Rainbird Software, First Floor, 74 New Oxford Street, London WC1A 1PS
Tel: 01-240 8838

KNIGHT Orc is Level 9's latest release under the Rainbird label and is a major step forward in adventure sophistication.

The game is large – so much so that it is split into three separate parts. Because it is so big there is no room left for graphics – for Atari 8 bit owners this version is text only.

In most adventures the role of the hero or heroine is normally taken over by the player. Not so in Knight Orc. True, you do play the main part but in this case the star is an ill-smelling, cowardly Orc by the name of Grindleguts.

Orcs have been persecuted by adventurers for generations – is it possible that you now have a chance to get your own back?

The game starts in splendid style with you being challenged to a fight by a human knight. Only trouble is someone has tied you to your horse so you can't run away, much as you'd like to.

Apparently your erstwhile Orc chums did this to you while you were intoxicated, volunteering you as their champion while you snored on.

Because you're a yellow-streaked, somewhat repellent streak of Orcanity you'll be spending much of your time running away from potential duffings up. It seems at times as if the entire population has got a personal grudge against you.

And that's possibly one of the drawbacks with the game. Although a generous helping of personalities is to be desired in an adventure there are so many characters in Knight Orc (over 70 I believe) that at times you become a little bewildered by all the to-ing and fro-ing, fighting and fleeing.

The huge cast list includes such notables as Rapunzel, the Green Knight, the Annihilator, Brunhilde, Green Sleeves, Jabberwock, Kris the Ant Warrior, Mrs Wallop, Synonym the Wizard and Professor Nuttar. Not to be taken too seriously, you see.

Another unusual feature is that no mapping is required. You need simply state where you want to go (major locations are mentioned in the text), and the program will take you step by step along the appropriate route. Go, run and find are the main commands for movement – you can also use them to locate objects which you have previously seen or mislaid.

Characters can be talked to, commanded, followed and even ambushed – the powerful parser allows you to carry out such interesting actions as: Wait for the innkeeper and attack him.

Simultaneous action is possible. For example, you can instruct a character to go off and find something. At the same time as that person is carrying out your instructions, you can continue with your own business.

Magic is also at work in Knight Orc. There are 21 spells to find and learn and they can be used in unexpected ways. In addition all is not as it first seems in this game.

Although the plot casts you in the role of an oppressed Orc whose prime objective in Part I is to stay alive long enough to collect enough lengths of rope to cross a bridge into Part II, once there the notion may slowly dawn on you that something very strange is going on.

There's a neat twist to this adventure but you'll have to discover it for yourself.

As well as a large cast list Knight Orc has a vast number of locations. Many are fairly predictable (a wide range of similar arboreal spots in Part I for example). In this respect the game could have done with a bit of tightening up. Given the quantity of characters and locations, the nature of your initial task and the arbitrary nature of the characters' appearances, Knight Orc has a somewhat unstructured and sprawling feel to it at the beginning. However, perseverance pays off – Parts II and III are better in this respect.

As well as detailed and stimulating text, a powerful parser and a massive vocabulary, the game also has the usual save and restore features including ram save and restore.

Knight Orc has its flaws, the too large cast list and the too frequent random appearances of the characters being chief among them.

But having said that, the adventure has a lot to offer and is certainly one of the most sophisticated around.

On strict value for money terms, you get a great deal of high quality material, entertainment and play for your cash.

Knight Orc can be a little frustrating and unsatisfying in its early stages but the game is so big and complex that if you persevere you'll be well pleased with this addition to your adventure collection.

Bob Chappell

Presentation	*8*
Atmosphere	*7*
Puzzlement	*8*
Value for money	*8*
Overall	*8*

COMING SOON...

To further augment your adventure library you should be on the look out for two new titles from Rainbird. They are offering the more adventurous of you Time and Magik and Jinxter.

Time and Magik is from the Level 9 team of Mike and Pete Austin. Indeed Level 9's heroine, Ingrid Bottomlow, will be making her adventuring debut any day now in her first role as the Gnome Ranger.

Plundered Hearts, and Nord and Bert Couldn't Make Head Nor Tail Of It, the two new Infocom titles, are also on the edge of release. Ruoloc is looking into them.

No jump for joy

Program Leapster
Price £9 95 (disc) £7 95 (cassette)
Supplier Red Rat Software
11 15 Fennel Street Manchester M4 3DU
Tel 061 835 1055

I HAD high hopes for Leapster as it loaded The introductory screen was rather attractive and a nicely harmonised little tune was playing at a fair lick

I pressed fire to start as instructed I was greeted by a street scene a little naive in its rendition perhaps but inoffensive enough

The jaunty tune had slowed to a turgid drone and this was to get progressively more annoying as the game wore on

Jimmy the Leapster was standing in the middle of the road on the way to school Someone's mum hadn t taught him the Highway Code that s for sure

He is apparently on his way to school to free his headmaster

Anyway there he is under your control looking like some demented leprechaun, bowling down the street heading towards on rushing motor cars

Looking at the houses you see various objects shown fleetingly at one of the four windows in which they may appear

Jimmy must jump on to the cars riding them until next to a window with something in it and then leap at it to grab the object and be awarded points

He needs to collect objects to progress to the next level

As you have probably guessed, the level after the High Street is the Nuclear



Missile Site most kids stroll through one on their way to school don t they?

After the missile site there is the Haunted Cemetery and then the school itself

The pace is on the slow side and once the leaping or to car bonnet stunt is mastered there is little to offer a challenge

I am afraid that I found the story line a little disjointed but maybe Red Rat will alter this in the production copy The company has tried to make a dull game more interesting [illegible] including [illegible] supposedly exciting for a time but I m sorry to say that it doesn t work and I was left with the feeling that here was a game merely bashed out in time for Christmas

Red Rat is capable of producing better than this

Niels Reynolds

Sound	5
Graphics	7
Playability	6
Value for money	8
Overall	6

Don't nod off...

Program Nightmares
Price £9 95 (disc) £7 95 (cassette)
Supplier Red Rat Software
11 15 Fennel Street Manchester M4 3DU
Tel 061 835 1055

YAWN it was two in the morning and I was feeling pretty drowsy The disc drive whirred quietly and my eyes blurred I m not entirely sure what happened next but it was pretty weird

I looked at my TV screen and there I was posing like some errant fairy godmother, with a lovely pair of golden wings flapping behind me

Then things started happening Blue Airflits started buzzing round me like wasps around a jam pot sapping my energy as they touched

Fortunately my magic wand was loaded and I opened fire to try to persuade them to buzz off – but they kept on coming

Things were to improve however as I slowly became accustomed to my surroundings Somewhere deep in my subconscious I had the feeling that I must collect five little pink fairies in order to get into the next level of this strange experience

Unaccustomed as I am to going round picking up fairies I nonetheless steeled myself and set off on my quest – although quite what the ultimate aim of it was I still didn t know

Suddenly out of the ground emerged two Grunts They were ugly beasts looking like giant eggs on legs

These monsters spat globs of energy sucking venom at me and to make matters worse they were totally unaffected by my puny magic wand bolts

Luckily I had noticed that every now and then the



wand would shoot out a bomb which really cracked them up so some defence was at least possible

This particular task was made more difficult by the fact that the Grunts would usually survive a direct hit This was partly compensated by their falling to bombs dropping a short way ahead of them

Having picked up the fairies and despatched sufficient Airflits and Grunts, I bolted for the doorway to the next level Here I was confronted by enormous red dragons and long nosed flying sea horses which needed repeated shooting in order to kill them

The [illegible] the dragons would get me more often than not but I kept coming back for another go

I woke up with a start In front of me lay a pre release copy of Nightmares a new title from Red Rat

It was four in the morning and I was feeling pretty drowsy The disc drive whirred quietly and my eyes blurred

Paul Mills

Sound	6
Graphics	7
Playability	8
Value for money	7
Overall	8

Button up for the battle

GEORGE O'DONNELL takes a look at an alternative joystick

JOYSTICKS can cause endless problems – they don't move quickly enough and they also wear out rapidly Star Trek is a small hand held pad which puts all possible stick-position and firebutton combinations on to individual keys to overcome these problems So, for example you can select "up-left" or "up-left plus fire" with a single touch

It's not the first keypad to hit the market and some of the others have left a lot to be desired so I was initially sceptical about testing this one However after playing with it for an hour or two, I found myself getting hooked and wondering why no one has marketed anything quite like this before

The first thing you notice is that the pad is easy and comfortable to use It is equally suitable for left or right handed players and the buttons have a crisp positive feel to them

I expected that it would take an hour or two to get used to the key layout but in fact I was blasting away at full speed after only about 15 minutes – which was when I noticed how much it reduces wear and tear on the wrist and trigger finger

The next thing that hits you is the pad's responsiveness You know how tricky it can be to get Bounty Bob into precisely the right position before he jumps? Well it's a doddle with this controller – you can move him a couple of millimetres at a time simply by touching the key briefly Far more accurate and sensitive than a joystick

The pad also eliminates a major bane of the arcade game player's life Unreliable diagonal movement Conventional sticks are prone to this problem because they contain only four switches Up, down left and right

To get diagonal movement two adjacent switches must be levered down simultaneously and if you get the stick position slightly wrong only one of the two gets pressed The result is horizontal or vertical rather than diagonal movement – very frustrating on games which give you limited space to manoeuvre

With the Star-Trak pad this can't happen since there is only one key to press for diagonal movement An electronic decoder generates the correct signal so you can't get it wrong

Another useful feature is a central extra fire button which has three functions controlled by a slide switch With this switch set to normal, a single touch on the central button produces a single shot which will always deliver, no matter how briefly you press the button

Set the switch to Auto and you get conventional auto fire which blasts away without your touching any key

But there's also a centre position which gives you Burst action – press the button and you get auto fire, release it and firing stops

Where this controller really scores though, is on the latest generation of sports simulations – Karate and Olympics clones – which rapidly hammer joysticks to death and require complex position and/or fire button combinations

It has now been extensively consumer tested – by me my wife two children and the cat – and with one furry exception all participants managed to beat their previous high scores on several arcade games so we're very happy with it

The controller isn't perfect for every program, though Conventional joysticks give a more authentic feel on flight and driving simulations, and one or two games involve rotating the joystick rapidly around its eight positions which is very tricky to do with Star Trak

It's worth hanging on to your old joystick for games like these but for many others, especially the latest generation, the new pad appears to have a definite edge There are also two other things worth mentioning

First it comes complete with a three metre lead which plugs into the pad rather than being wired permanently in place You can use this lead with conventional joysticks, or paddles or anything else that plugs into a joystick port – including Len Golding's gadgets Nice bonus that

Second the pad is made entirely in this country and it is evident from the design and construction – yes I took the back off – that it is built to last

The switches are all genuine keyboard 'click' types – not a rubber membrane in sight – and the rest of the mechanism is solid-state so there's very little to go wrong In fact the manufacturers guarantee it for 12 months which is a good measure of their confidence

All this makes the price tag of £18 85 look quite reasonable – if it outlasts two joysticks you've made a profit! And I can see these controllers turning up in a great many Christmas stockings this year

Product Star Trak
Price £18.85
Supplier RH Design 137 Stonefall Avenue Harrogate North Yorkshire HG2 7NS
Tel 0423 880520

SNOWBALL

By MATTHEW BERNSTEIN and CASPIAN PRINCE

HERE is a fascinating puzzle game where you take the part of Snowy, a small white snowball trapped inside an ice maze You want to get outside to play in the snow, but to do this you must solve the secrets of the maze as you look for the solitary secret exit

To move Snowy you can either use a joystick plugged into port one or the keyboard The keys to use are Y for up B for down G left and H right If you get stuck at anytime during the game press the spacebar to melt Snowy and start again

As you roll around the maze you will notice that Santa has dropped some of his presents and you can pick them up Each will allow you to traverse a different segment of the maze and may help or hinder you – but this is for you to figure out

While you're empty-handed you leave a trail of snow behind you and this freezes creating an invisible barrier Once you've picked up a present the trail becomes coloured

Santa has also left these clues

- Do you need all my presents?
- Think where you want to go
- Some ice is melting
- What colours are my presents?
- Merry Christmas!

When you type in the program be sure to use Get it Right III to ensure that you have entered it correctly

And don't forget to save a copy before you run it as the program uses DLIs which may crash the computer if you make an error

Turn to Page 21 ▶

Mini Office II
6 powerful home and business programs in just ONE package – at a price that simply can't be matched!
Voted Business Program of the Year – 1985 AND 1986
'This package is incredible value
Mini Office II

◄ From Page 19

PROGRAM BREAKDOWN

80 – 140	Title
150 – 220	Character set redefined
230 – 280	DLI to flash title
290 – 580	Draw maze and presents
590 – 990	Main loop
1000 – 1210	Escape from the maze routine

VARIABLES

X Y	Coordinates of snowball
XM YM	Movement of the snowball
C, D, P	What the snowball is on
NO OBJ	Presents the snowball has collected
SWF	Melting snow
CH	Type of snow trail
A, A$	Key input
DL	Display list pointer
RT RM	Character set pointers

```
10 REM SNOWBALL
20 REM BY MATTHEW BERNSTEIN
30 REM 600 CASPIAN PRINCE
40 REM (C)ATARI USER
50 GRAPHICS 17 POKE 16,64 POKE 53774,6
4 POSITION 6,27 POKE 731,1 POKE 711,0
60 REM TITLE SCREEN
70 GOSUB 540 POKE 756,RT
80 ? #6,"[illegible]" REM 200 CTRL-F,CTRL
-G,CTRL-H,CTRL-I,CTRL-J,CTRL-K,CTRL-L,
CTRL-L
90 FOR I=0 TO 15:SOUND 0,269,6,I SOUND
 1,0,0,I POKE 711,I FOR J=1 TO 20:NEXT
 J NEXT I
100 FOR I=15 TO 0 STEP -1 SOUND 0,269,
6,I SOUND 1,0,0,I:POKE 711,I FOR J=1 T
O 20:NEXT J NEXT I
110 POKE 559,0
120 GOTO 200
130 REM INITIALISE SCREEN
140 POKE 559,0
150 REM REDEFINE CHARACTERS
160 REM (MOVE NEW SET)
170 RT PEEK(106) 8 RM=RT*256
180 DATA 0,0,0,0,0,0,0,0,102,60,126,
126,60,102,0,0,0,24,231,231,0,231,231,
0,16,100,100,0,100,183,200
190 DATA 0,102,60,126,126,60,102,0,0,6
0,122,126,126,126,60,0,63,127,192,254,
127,31,254,252
200 DATA 59,115,123,127,127,111,103,99
,62,127,127,119,119,127,127,62,99,107,
107,127,127,127,119,99
210 DATA 126,127,115,120,127,119,127,1
26,20,62,227,119,99,127,127,98,112,112
,112,112,112,112,127,127
220 FOR I=0 TO 103 READ D POKE RM+I,D
NEXT I
230 REM SET UP A DLI
240 DATA 72,173,10,210,141,20,141,20,2
12,141,22,200,104,64
250 FOR I=1536 TO 1549:READ D POKE I,D
:NEXT I
260 DL=PEEK(560)+256*PEEK(561):POKE DL
+24,134:POKE 512,0:POKE 513,6 POKE 542
86,192:POKE 659,34
270 RETURN
280 POSITION 0,0
290 REM DRAW SCREEN
300 ? #6,"||||||||||||||||||||",
310 ? #6,"|  |    y |      |",
320 ? #6,"| | | |  |      |",
330 ? #6,"|   || |||  ||  |",
340 ? #6,"| | ||  | |    | |",
350 ? #6,"| |   | || |    | |",
360 ? #6,"| ||| | | | |   | |",
370 ? #6,"| |   ||$| | |  | |",
380 ? #6,"| | |   |  | |  | |",
390 ? #6,"| | |||||||||   | |",
400 ? #6,"| |   |         | |",
410 ? #6,"| | | |         | |",
420 ? #6,"| | | |||||||||  | |",
430 ? #6,"| |   |    |     | |",
440 ? #6,"| ||||||$|| |  | | |",
450 ? #6,"| |    |  ||||  | |",
460 ? #6,"| || || | |   | | |",
470 ? #6,"|||| || | | | | | |",
480 ? #6,"| |    | |  |   | |",
490 ? #6,"||||||||||||||||||||",
500 REM Lines 270 & 310 . CTRL-
510 REM Lines 310 & 410 . CTRL-
520 REM Line 310 . Control-
530 POKE 709,52 POKE 710,198 POKE 711,
134 POSITION 6,22
540 ? #6,"&'()*+,," REM INV CTRL-F,CTR
L-G,CTRL-H,CTRL-I,CTRL-J,CTRL-K,CTRL-L
,CTRL L
550 POKE 756,RT:POKE 708,0 POKE 559,34
560 FOR I=0 TO 15 SOUND 0,250,I,15-I P
OKE 708,I:FOR J=1 TO 20 NEXT J NEXT I
570 X=9 Y=1 C=7:D=0 SWF=0
580 OPEN #1,4,0,"K:" DIM A$(1) 0=7
590 REM MAIN LOOP
600 POKE 77,0 IF PEEK(764)<>255 THEN G
ET #1,A:A$=CHR$(A):GOTO 630
610 IF STICK(0)<>15 THEN A$="":GOTO 63
0
620 GOTO 600
630 IF A$="Y" OR STICK(0)=14 THEN YM=-
1:XM=0 GOTO 690
640 IF A$="B" OR STICK(0)=13 THEN YM=1
:XM=0 GOTO 690
650 IF A$="G" OR STICK(0)=11 THEN XM=-
1:YM=0 GOTO 690
660 IF A$="H" OR STICK(0)=7 THEN YM=0:
XM=1 GOTO 690
670 IF A$=" " THEN RUN
680 GOTO 600
690 D=C LOCATE X+XM,Y+YM,P IF P=33 OR
P=155 THEN 800
700 IF P=2 THEN C=1:GOTO 850
710 IF P=162 THEN C=2:GOTO 850
720 IF P=130 THEN C=1 GOTO 850
730 IF P=3 THEN C=4 GOTO 850
740 IF P=3 THEN C=3 GOTO 850
750 IF P=163 AND C=4 THEN C=5 GOTO 850
760 IF P=160 AND C=5 AND OBJ=5 AND SWF
 THEN 1020
770 IF P=260 THEN NO=1 GOTO 85
0
780 IF P=32 OR P=131 THEN NO 1 GOTO 85
0
790 IF P=1 AND (C=2 OR C=6) THEN NO=1
GOTO 860
800 IF P=129 AND C=1 THEN NO 1 GOTO 85
0
810 IF P=129 AND C=4 THEN NO=1 GOTO 85
0
820 IF P=36 AND C=6 THEN SWF=1 NO=1 GO
TO 650
830 IF P=161 AND C=5 THEN NO=1:GOTO 85
0
840 SOUND 0,0,4,0 SOUND 0,100,4,8:FOR
X=1 TO 10 NEXT I SOUND 1,0,0,0 SOUND 1
,0,0,0 GOTO 600
850 IF C=1 THEN CH=1 GOTO 920
860 IF C=2 THEN CH=161 GOTO 920
870 IF C=3 THEN CH=129 GOTO 920
880 IF C=4 THEN CH=3 GOTO 920
890 IF C=5 THEN CH=128 GOTO 920
900 IF C=6 THEN CH=161 GOTO 920
910 IF C=7 THEN CH=128 GOTO 920
920 FOR I=10 TO 0 STEP -2.5 SOUND 0,0,0,
I NEXT I
930 POSITION X,Y ? #6;CHR$(CH):X=X+XM
 Y=Y+YM POSITION X,Y ? #6,"*" GOTO 6
00
940 IF P=131 THEN OBJ=OBJ+1:FOR X=255
TO 0 STEP -10 SOUND 0,I,10,6:NEXT I SO
UND 0,0,0,0
950 IF NO=0 THEN OBJ OBJ-1 IF C<>5 THE
N FOR I 255 TO 0 STEP -16 SOUND 0,I,10
,6 NEXT I SOUND 0,0,0,0
960 IF NO(1)<0 THEN 600
970 SOUND 0,242,10,8 SOUND 1,121,10,6
SOUND 2,40,10,8 SOUND 3 29,10,6 FOR X=
1 TO 50 NEXT I
980 SOUND 0,0,0,0 SOUND 1,0,0,0 SOUND
2,0,0,0 SOUND 3,0,0,0
990 GOTO 600
1000 REM [illegible]
```

Turn to Page 22 ►

◄ From Page 21

```
1010 REM FINISHES THE GAME
1020 FOR I=15 TO 1 STEP -1
1030 FOR P=0 TO 255 STEP 20
1040 SOUND 0,P,4,I
1050 POKE 709,I:POKE 705,I*40:POKE 710
,I*192:POKE 711,I*128:NEXT P:NEXT I
1060 GRAPHICS 17:POSITION 6,8:POKE 711
,0:POKE 756,AT:POKE 708,0
1070 ? #6;"▲▼▙▟":REM INV CTRL F CT
RL G,CTRL-N,CTRL I,CTRL J,CTRL K,CTRL
L,CTRL-L
1080 ? #6;"":? #6;"  MERRY CHRISTMAS
!"
1090 FOR I=0 TO 15:SOUND 0,255,6,I:SOU
ND 1,0,0,I:POKE 711,I:FOR J=1 TO 20:NE
XT J:NEXT I
1100 FOR I=15 TO 0 STEP -1:SOUND 0,255
,6,I:SOUND 1,0,0,I:FOR J=1 TO 20:NEXT
J:NEXT I
1110 DL=PEEK(560)+256*PEEK(561):POKE 5
4286,64:POKE DL+6,134:FOR J=1536 TO 15
46:READ D:POKE J,D:NEXT J
1120 DATA 72,169,224,141,10,212,141,9,
212,104,64
1130 POKE 512,0:POKE 513,6:POKE 54286,
192
1140 FOR I=0 TO 3:POKE 708,0:FOR J=0 T
O 10:NEXT J:POKE 708,12*I:FOR J=0 TO 3
0:NEXT J:NEXT I
1150 FOR I=1 TO 30:READ A0,A1,D:SOUND
0,A0,10,6:SOUND 1,A0+1,10,6:SOUND 2,A1
,10,4:SOUND 3,A1+1,10,2
1160 FOR J=1 TO D*20:NEXT J:SOUND 2,0,
0,0:SOUND 3,0,0,0:SOUND 2,A1,10,4:SOUN
D 3,A1+1,10,2:FOR J=1 TO D*20:NEXT J
1170 SOUND 0,0,0,0:SOUND 1,0,0,0:SOUND
 2,0,0,0:SOUND 3,0,0,0:NEXT I
1180 DATA 91,91,1,60,108,1,60,108, 4,6
0,108, 4,60,108, 4,72,108, 4,81,102,1,
81,102,1,81,102,1,60,96,1,60,96, 4,53
1190 DATA 96,,4,60,96, 4,60,96, 4,72,9
1,1,91,91,1,91,91,1,81,60,1,53,60, 4,5
0,60, 4,53,60, 4,60,60, 4,60,102,1,81
1200 DATA 108,1,91,91, 4,91,91, 4,81,1
02,1,60,53,1 2,72,91,1 4,60,128,6
1210 GRAPHICS 0:POKE 764,255:END
```

Get it right! II

10 CP1 (Y)	210 X64 (F)	410 H9K (A)
20 CP2 (3)	220 NR4 (X)	420 4JJ (P)
30 CP3 (X)	230 R7I (X)	430 4GL (4)
40 CP4 (6)	240 US0 (S)	440 4XH (9)
50 N01 (0)	250 NKW (0)	450 4LP (U)
60 CP6 (R)	260 8CA (P)	460 4G0 (R)
70 6AK (0)	270 S26 (X)	470 4UF (S)
80 R90 (J)	280 Y30 (1)	480 S1E (8)
90 C5H (E)	290 NYT (B)	490 5HC (S)
100 P3K (2)	300 40A (F)	500 CUW (L)
110 S0T (0)	310 874 (B)	510 CYW (S)
120 8S7 (A)	320 45J (X)	520 13W (K)
130 47S (0)	330 8L9 (0)	530 3MS (0)
140 SMY (Y)	340 47C (F)	540 0EK (A)
150 N69 (L)	350 4NN (0)	550 7SV (C)
160 9L9 (X)	360 443 (I)	560 ATJ (3)
170 R03 (P)	370 5A0 (1)	570 AG4 (E)
180 TYM (C)	380 C4K (2)	580 ULR (K)
190 0H0 (H)	390 59J (E)	590 0YM (V)
200 T7I (Q)	400 3NF (S)	600 0AC (X)

610 9A7 (V)	810 75T (1)	1010 0ON (E)
620 950 (C)	820 HRS (A)	1020 G0M (P)
630 4HR (0)	830 76T (3)	1030 LRL (P)
640 3M0 (4)	840 6XJ (U)	1040 361 (9)
650 185 (6)	850 LR9 (0)	1050 R77 (A)
660 896 (K)	860 UPC (Y)	1060 PIN (D)
670 9C1 (0)	870 UXC (A)	1070 U4V (1)
680 AJ0 (K)	880 AH0 (Y)	1080 03Y (P)
690 10W (E)	890 VF3 (U)	1090 7J1 (B)
700 LLF (Y)	900 UF0 (L)	1100 78S (V)
710 LRT (9)	910 UP4 (L)	1110 USV (X)
720 LJA (A)	920 47R (Y)	1120 767 (O)
730 M9F (W)	930 PEE (M)	1130 4T3 (F)
740 M3F (8)	940 HY1 (C)	1140 HW7 (6)
750 3J2 (M)	950 2EV (G)	1150 U4E (E)
760 SWV (M)	960 JA8 (1)	1160 813 (H)
770 0RJ (L)	970 13K (P)	1170 UY4 (7)
780 SAF (R)	980 C0V (H)	1180 ASM (J)
790 R3A (1)	990 AHG (E)	1190 901 (0)
800 6YC (U)	1000 CXN (C)	1200 AA4 (P)
		1210 W53 (9)

Bargain basement

ALAN GOLDSBRO expands his Atari's DTP capabilities with The Print Shop Companion



DESKTOP Publishing is all the rage now, but for many users it was the 8 bit Atari and Print Shop which gave them an insight into this field. Print Shop from Broderbund was made available in late 1985 and ever since then it's been the only usable Atari 8 bit program within the desktop publishing format.

Not to be outdone by its 16 bit cousins where this type of program is very popular, Broderbund has released The Print Shop Companion as the perfect partner for The Print Shop.



Main menu

Like the Print Shop, the Companion is easy to use, foolproof and a whole lot of fun. It expands the capabilities of Print Shop and adds a series of Editors, new Fonts, Borders and Icons. Even though you can use the Companion as a standalone program, to get the most from it you'll need to have The Print Shop.

To achieve true compatibility, the original Print Shop disc has to be modified by the Companion – this means updating selective files so it can recognise borders and fonts from the Companion, and the Companion copies the set up information from the Print Shop disc to the Companion disc.

Once this has been achieved the original blue background colour of the Print Shop should turn to black.

The Print Shop Companion is as easy to use as the original Print Shop and follows the same menu driven system. Working from the menu the first option is the Graphic Editor+. This has all the commands of the original editor – with one exception: The wrapround cursor.

The extra commands available make up for this though – four mirror modes, text, and numbers, insert/delete row/column, flip horizontal or vertical, negative (black) or positive (normal), line commands, rays, boxes and ovals. There is even a locking mode for drawing, plus 17 fill patterns, a flood fill and a very welcome undo key.

The best feature has to be the Super Impose key. Icons can be placed side by side or top to bottom on the one screen, then saved to disc as a complete icon – marvellous!



Creature maker menu



Font editor menu

The best way to visualise this is when when working with the date format. There are 20 number graphics, 0 – 9 in both left and right positions and the four date endings – st, nd, rd and th. All can be superimposed and making a date such as 20th has never been so easy.

There are 50 new border selections to choose from on the Print Shop Companion disc and if you ever get tired of them you can always create your own with the Border editor.

The editing area consists of three edit boxes, representing the four corners, top and bottom, and the sides respectively. There are x and y coordinations to help you in placing the pixels in the grid. As you draw, the border is displayed as a whole unit which gives you an overall view of how the completed unit will look.

You can copy any of the edit boxes to another one, but unfortunately this does not let you retrieve graphic icons and place them in the edit boxes.

There are a number of commands available such as Get, Save, Print, Clear and Lock – these are standard features right the way through the Companion disc. Of the other commands, flip horizontal, vertical, or negative are as you would expect, and the bottom and right sections of the border can be flipped to make a mirror image of the top and left sides of the border respectively.

The Companion's Font Editor lets you add your own personalised fonts, either by editing any of the 20 fonts from Print Shop and Companion or by designing your own. The creation of fonts is a complicated and time consuming process which can really test your dedication to computing!

If you wish to edit a font, say to add a £ sign – because its an American

Turn to Page 24 ▶

◄ From Page 23

program there s only the $ or perhaps a series of graphical characters instead of text, then load up an existing font and edit away

To create an entirely new font takes considerable patience and an understanding of how text is created in the first place – the best way is to use the built in reference font

This comes in three sizes Small, medium or large The larger the font the greater the memory used – a small font takes up about 27 per cent while a large font can use up to 90 per cent of file memory

Designing or creating fonts is difficult, but there are plenty of commands available to assist you Should you begin to master the font editor there is even a command to flip the font backwards

The Tile magic feature provides an array of 11 moving patterns very similar to the kaleidoscopes in the original Print Shop Unlike the kaleidoscopes though these can be saved to disc or passed directly to the Graphic Editor+ where you can add your own touches The tiles can be made to enhance backgrounds by flooding them together before superimposing text on your card and poster layouts

In similarity Creature Maker allows you to create original graphics by mixing and matching body parts There are 1000 possible combinations which can be saved to disc and like the tile magic passed instantly to the Graphic Editor+ for personalised touches

Print Shop Companion has an excellent calendar facility, creating either weekly or monthly calendars with Print Shop graphics and choice of fonts The calendar has a date range from 1753 to 9999 Graphics can be positioned across the top of the page in two sizes Text choices are from standard outlined or 3D and it can be placed in each day to highlight important events up to a 120 characters for each day in the weekly versions and 112 characters for the monthly one

Finally, not only can your designs be printed out but they can also be saved to disc and edited as and when required

There are a couple of mini features to Print Shop Companion which don t really fit a specific category For example there are 20 bonus graphics from Broderbund software characters and you have the opportunity to leave Print Shop Companion and load up the Print Shop disc without rebooting

Using Print Shop is tremendous fun and with the addition of Print Shop Companion, Broderbund has made an excellent package for the Atari 8 bit market. I feel the Tile magic and Creature maker are mainly for the kids – certainly they won t get used much by me – but on the other hand the calendar is brilliant, the Graphic Editor+ a wondrous improvement on the original and the border and font editors extremely welcome

If you ve already got Print Shop then buying the companion will be money well spent If you are without then there s a whole lot of exciting projects out there just waiting for you to try Your printer will never forgive you for missing it!

Product. The Print Shop Companion
Supplier. Broderbund/US Gold Units 2/3 Holbard Way Holbard Birmingham B6 7AX
Tel 021 356-3388
Price £20 95

The USR function

LEN GOLDING concludes his look at this powerful command

LAST month we looked at USR in its simplest form: X=USR(ADDRESS). But you have probably come across listings which contain far more complex statements such as X=USR(ADDRESS,100,A,B*5). Let's look how extra numbers and variables like these can be used in your own programs

No matter how many things there are in the brackets, the first one is always the address of your machine code routine. It can be a real number, a variable name or an expression – such as ADR(A$) or 256*PEEK(106) – so long as its value is equal to the exact start address of your routine. All the other values in the brackets are called *parameters* or *arguments*.

As far as USR is concerned they are just ordinary numbers, not addresses or machine code instructions or anything else complicated. You can have up to 127 different parameters and each one can be a real number, a variable name or an expression, so long as its value does not exceed 65535.

The USR function automatically stores these parameters in a form that can easily be retrieved by your machine code routine. So you can use Basic to do calculations which machine code finds difficult – complex arithmetic for example – then transmit the result to your machine code routine for action.

This simplifies the machine code programming enormously, so it's a worthwhile technique to master. Here's how it works.

The 6502 processor uses a special memory area known as the Stack – think of it as a long vertical tube closed at the bottom end. Data can be pushed into it or pulled out of it one byte at a time, but you have access only to the one on top. If you wanted to retrieve, say, the third byte down you would first have to remove the top two bytes.

Now the first thing USR does is to note its current position in the Basic program, so that it can return later, and pushes this two byte address onto the stack, low byte first.

Next it takes the parameters in turn, reading from right to left, and converts each into a two byte integer. The parameter divided by 256 gives the high byte, and the whole number part of whatever remains is the low byte.

It pushes each of these two-byte values on to the stack, low byte first, and finally puts one more byte on top of the stack, to show how many parameters there were in the USR statement.

```
10  *=$600
20  PLA      Discard number of parame
ters (=1)
30  PLA      Discard high byte of para
meter (=0)
40  PLA      Low byte = required scree
n colour
50  STA 710  Store it in the colour re
gister
60  RTS      Return to Basic
```

Program I: Modified screen colour change routine

```
10 FOR X=0 TO 6:READ B:POKE 1536+X,B:N
EXT X
20 DATA 104,104,104,141,198,2,96
30 C=10:REM Desired screen colour, 0 t
o 255
40 X=USR(1536,C)
```

```
10 NW6 (6)
20 JVE (7)
30 NBJ (K)
40 SN2 (C)
```

Program II: Basic loader for Program I

Let's look at some examples. Remember our simple colour change routine from last month? It changed the screen from blue to black when you typed X=USR(1536). By adding a parameter and modifying the machine code program slightly you can make the screen change to any colour you want.

Program I shows the new routine and Program II is the Basic translation.

The routine is called using X=USR(1536,C), where C is a number from 0 to 255 which will control the screen colour. On execution of this statement the stack will start off looking like this:

Top of Stack

1		number of parameters
C	Hi	high byte of colour parameter (must=0)
C	Lo	low byte of colour parameter (0 to 255)
R	Hi	high byte of return address
R	Lo	low byte of return address

It is vital to remember that every parameter pushes two bytes on to the stack, even if it's only a one-byte number (less than 255), and that the number of parameters is pushed on to the top of the stack even if that number is zero.

The machine code in program I starts with three PLA instructions. Each of these removes one byte from

Turn to Page 27 ▶

```
10 CDTMA2=$228
20 CDTMV2=$21A
30 CHACT $2F3
40  *=$600
50 ;This routine is called by X=USR(1
536,SWITCH,RATE) SWITCH controls the
60 , ON/OFF function, RATE controls th
e flash frequency Neither number may
exceed 255
70 SETVEC
80  PLA                  Number of
 parameters (-2)
90  PLA                  High byte
 of SWITCH (-0)
0100  PLA                Low byte
of SWITCH
0110  STA CONTROL        - on or
 off command
0120  PLA                High byte
 of RATE (-0)
0130  PLA                Low byte
of RATE
0140  STA DELAY          - desired
 flash rate
0150  LDA #START&255     Tell the
computer where the
0160  STA CDTMA2         blink r
outine starts - it
0170  LDA #START/256         will JSR
through this address
0180  STA CDTMA2+1           when CDTM
V2 counts down to 0
0190 START
0200  LDA CONTROL            Flash now
time wanted?
0210  BNE BLINK              Branch if
 yes
0220  LDA #2                 Else make
 sure cursor
0230  STA CHACT              is opaque
0240  RTS                    and retur
n to Basic
0250 BLINK
0260  LDA CHACT              Read cont
ents of 755
0270  EOR #2                 Change fr
om 2 to 0
0280  STA CHACT
0290  LDA DELAY              Reset fla
sh rate every
0300  STA CDTMV2             time the
routine is called
0310  RTS                    Return to
 Basic
0320 CONTROL *=*+1
0330 DELAY *=*+1
```

Program III: Modified flashing cursor routine

◀ From Page 25

the top of the stack and puts it into the 6502 Accumulator Line 20 removes the number of parameters byte, which is of no interest to us so we don t do anything with it

Line 30 takes out the high byte of our parameter which in this particular case must be 0, since you can t store more than 255 in a colour register So, again it is discarded

The final PLA retrieves the parameter s low byte which is the true value of C, and line 50 stores it into colour register 2 The RTS instruction at line 60 pulls the two remaining bytes off the stack converts them into a two byte address, and terminates the USR routine by jumping to that address in ram

All being well, this will restore control to your Basic program at the statement immediately following the USR call

Everything above the return address must be removed from the stack before the final RTS is executed otherwise the computer will wander off into never never land and your program will crash

That's why every USR routine must contain at least one PLA instruction – to remove the number of parameters byte – even if there are no parameters

Programs III and IV are a bit more interesting They are based on last month's flashing cursor routine By using parameters you can gain control over the flash rate, and switch the routine on or off at will

The variable *SWITCH* turns the routine off if it s zero or on if it a non zero, while *RATE* controls the flash frequency Neither parameter may exceed 255, so at the start of this routine the stack will look like this

2	Number of parameters
SWITCH Hi	High byte of SWITCH (must=0)
SWITCH Lo	Low byte of SWITCH
RATE Hi	High byte of RATE (must=0)
RATE Lo	Low byte of RATE
R Hi	High byte of return address
R Lo	Low byte of return address

Notice in Program III how the parameters are pulled off the stack in turn, and used by the machine code routine

Programs V and VI contain a simple routine for wiping a specified area of ram – useful when you re setting up player/missile graphics or page flipping The example given clears four pages (1024 bytes) of ram starting at address 20000 but you can change the parameters to suit yourself

```
10 FOR X=0 TO 46:READ D:POKE 1536+X,D:
NEXT X
20 DATA 104,104,104,141,47,6,104,104,1
41,48,6,169,21,141,40,2,169,6,141,41
30 DATA 2,173,47,6,208,6,169,2,141,243
,2,96,173,243,2,73,2,141,243,2
40 DATA 173,48,6,141,20,2,96
50 SWITCH=1 REM Set flash routine ON (
0 means OFF)
60 RATE=0 REM Set flash frequency (0 t
o 255)
70 X=USR(1536,SWITCH,RATE)
```

```
10 TSI (8)   50 UEL (B)
20 MDT (R)   60 UBB (N)
30 EVS (G)   70 JLC (4)
40 HSL (E)
```

Program IV Basic loader for Program III

In this example the parameter values exceed 255 so both bytes of the integer are relevant If you can work out how the stack operates in this routine you ve mastered the technique of parameter passing

Having come this far, you will now want to write routines of your own and this involves translating machine language source code into Basic DATA statements

Doing this by hand is tedious and error prone so as promised last month Program VII is designed to do all the hard work for you

First write your source code and check that it assembles correctly Next store it on disc or cassette in assembled form – this is the object code file There s a bug in Atari s Assembler Editor cartridge which makes it difficult to assemble a program directly to cassette so assemble it to ram first then use SAVE #C to make the cassette file

Disc systems do not have this problem you can use ASM #D [filename] to create the object file in a single operation Now go back into Basic, run Program VII and follow the instructions as they appear on the screen Your source code will be turned into DATA statements, complete with line numbers, which you then store in LISTed form so that they can be merged into any Basic program

Now you have mastered USR a whole new programming world is waiting You can use system timers, write vertical blank interrupt routines, experiment with fine scrolling customise parts of the operating system, talk directly to CIO, produce fast player/missile graphics and much much more

In fact you ve taken the first step along the road to becoming a fully fledged machine code programmer

```
10 ;Call by X=USR(1536,A,N)
20 START=$C0
30 *=$600
40  PLA              Number of paramet
ers
50  PLA              High byte of A
60  STA START+1
70  PLA              Low byte of A
80  STA START
90  PLA              High byte of N (=
0100  STA SIZE+1     Number of pages)
0110  PLA            Low byte of N (=
0120  STA SIZE       remaining bytes)
0130  LDA #0
0140  TAY
0150  LDX SIZE+1     Branch if less th
an
0160  BEQ REMAIN     1 page to erase
0170 LOOP
0180  DEY            Erase all complet
e pages
0190  STA (START),Y
0200  BNE LOOP
0210  INC START+1
0220  DEX
0230  BMI EXIT
0240  BNE LOOP
0250 REMAIN
0260  LDY SIZE       Erase remaining b
ytes
0270  BNE LOOP
0280 EXIT
0290  RTS            Return to Basic
0300 SIZE * *+2
```

Program V Erase N bytes of ram starting at address A

```
10 FOR X=0 TO 60:READ D:POKE 1536+X,D:
NEXT X
20 DATA 104,104,133,204,104,133,203,10
4,141,42,6,104,141,41,6,169,0,168,174,
42
30 DATA 6,240,12,136,145,203,208,251,2
30,204,202,48,7,208,244,172,41,6,208,2
39,96
40 START=20000 REM Start of RAM area t
o be wiped
50 BYTES=1024 REM Number of bytes to c
lear
70 X=USR(1536,START,BYTES)
```

```
10 ISF (4)   40 SAT (I)
20 T40 (S)   50 STK (E)
30 IMC (Y)   70 JYJ (7)
```

Program VI Basic loader for Program V

```
31999 REM PROGRAM 14: Converts object
code files into DATA statements.
32000 DIM A$(1),B$(16),C$(8),D$(12)
32010 ? CHR$(125) ? "Using disk or cas
sette? (D or C)";:INPUT A$
32020 IF A$="C" THEN B$="C:" C$="casse
tte":D$="object file" GOTO 32070
32030 IF A$="D" THEN B$="D:" C$="disk"
:GOTO 32050
32040 GOTO 32010
32050 ? ? "Input name of file ? "con
taining object code"
32060 INPUT D$ B$(LEN(B$)+1)=D$
32070 ? ? "Insert ";C$;" containing
";D$ ? "and press START"
```

Turn to Page 28 ▶

Program VII Convert code into DATA

◄ From Page 27

```
32080 GOSUB 32470
32090 OPEN #1,4,0,N$
32100 GET #1,X GET #1,X
32110 GET #1,X GET #1,Y
32120 START X+256*Y S=START
32130 GET #1,X GET #1,Y
32140 START=PEEK(106)-32 POKE 106,STAR
T GRAPHICS 0 START=START+256
32150 ? CHR$(125) ? START ADDRESS -
,S ?
32160 TRAP 32190 X=0
32170 GET #1,A POKE START+X,A
32180 X=X+1 GOTO 32170
32190 CLOSE #1
32200 TRAP 32200 POKE 752,1 ? ? NUMB
ER OF BYTES    X FINISH=START+X-1
32210 POSITION 2,16 ? Press START to
convert code into
32220 ? DATA statements for use by Ba
sic
32230 GOSUB 32470
32240 TRAP 32240 ? CHR$(125)
32250 ? At what line number do you wa
nt the ? DATA statements to start?
32260 INPUT LINE LSTART=LINE ? CHR$(12
5)
32270 BYTE=0
32280 ? ? ? LINE, DATA ,
32290 ? PEEK(START+BYTE),,,
32300 BYTE BYTE+1
32310 IF START+BYTE>FINISH THEN GOSUB
32490 GOTO 32350
32320 IF BYTE/20=INT(BYTE/20) THEN GOS
UB 32490 LINE=LINE+10   GOTO 32280
32330 IF BYTE/20=INT(BYTE/20) THEN ? C
HR$(126) LINE=LINE+10 GOTO 32280
32340 GOTO 32290
32350 ? Data encoding finished at lin
e ,LINE
32360 IF A$=  THEN A$ = DATAFILE TM
P
32370 ? ? 1  Insert new ,D$,  if ne
cessary
32380 ? ? 2  Press RETURN to create
the DATA file
32390 ? ? DATA statements recorded i
n this way
32400 ? may then be merged with any e
xisting
32410 ? program, using the command ?
 ENTER ,CHR$(34),D$,CHR$(34)
32420 POKE 752,0 POSITION 2,20
32430 ? LIST ,CHR$(34),D$ CHR$(34),
,,LSTART,,,LINE POSITION 2 18
32440 TRAP 32460
32450 END
32460 ? CHR$(125) ? ERROR  PEEK(195)
 GOTO 32370
32470 IF PEEK(53279)<>6 THEN 32470
32480 RETURN
32490 ? CHR$(126) ? CONT POSITION 2,
0 POKE 842,13 STOP
32500 POKE 842,12 ? CHR$(125) RETURN
```

Get it right! II

```
31990 EHN (  )   32250 WNE (S
32000 MAU (N)    32260 MAB (W
32010 WOW (W)    32270 TT  (U
32020 03R (U)    32280 HTP (N
32030 AWK (N)    32290 RCV (E
32040 UCS (G)    32300 WED (S)
32050 XVV (U)    32310 HX2 (7
32060 PPD (S)    32320 CDP (M)
32070 HLW (A)    32330 362 (E)
32080 WUE (C)    32340 UKN (7)
32090 SNV (L)    32350 WDR (L)
32100 GWR (1)    32360 E7H (W
32110 WKV (0)    32370 GJL (T)
32120 XBN (2)    32380 YNE (W
32130 SOV (G)    32390 JNY (3)
32140 AY9 (V)    32400 YSN (N)
32150 NWK (M)    32410 Q3Y (Y)
32160 RTP (N)    32420 RTH (L)
32170 NCH (5)    32430 77  (6)
32180 SEC (U)    32440 JTD (W)
32190 W7X (S)    32450 XP7 ( )
32200 BGL (6)    32460 QRR (G)
32210 REH (3)    32470 3HT (7
32220 EUL (L)    32480 YHS (
32230 WTY (C)    32490 TPE (S
32240 MX3 (A)    32500 71X  6
```

Your HINTS & TIPS

Feud

TO complete the game you must first go to the herb garden and try to collect as many herbs as you can before the gardener comes after you Then leave as fast as you can because your brother soon follows

Now go to the cauldron and mix the spells that are complete so you can use them against your brother – **William Gladwin, Doncaster, South Yorks**

Jet Boot Jack

WHILE playing this superb game from the English Software Company, if you are going across the slides and up the lifts push your joystick up then they will move faster Also play on the practice game as no monsters will appear to get in your way and annoy you – **Christopher Hussey, High Wycombe, Bucks**

Astromeda

THERE is a undocumented feature of the game If you stop your craft on top of the flashing area then your fuel will increase – **Kevin Campbell, West Lothian**

Atari Tennis

WHEN you are serving from the top of the screen in the one player game, always serve using a forehand as the opponent will have no chance of returning it – **Dinesh Bhudia, Harlesdon, London**

Alternate Reality

THERE are two healers and they work on alternate hours so, if a healer is out when you arrive wait until the next hour and try again It isn't worth fighting the brown mould as it only usually leaves you with a disease

There is nothing special about the clubs that you join, except that their prices are sky high The small green dragons and wraiths can be tricked, so you don't need to fight them

After using the healer his prices will increase so exit and walk back in again – **Granville Danby, Leeds**

Los Angeles Swat

ONCE you have fought your way to the crossroads you must fight off about four squads of men When the boss and the hostage appear, let them move on to the road When they are coming from the right just before the boss gets into your line of fire shoot and if you time it right and are very accurate, with luck you will kill him and miss the hostage – **Nigel Bowley, Hockley, Essex**

Pole Position

WHEN you start, keep the pause button pressed and this way your finishing time will be around 45 seconds – **Nicholas Atkins, Birstall Leicester**

Scrolls of Abadon

PLUG a joystick into port two type POW and after the game has started you can then move the creatures To change men press fire – **David Baxter, Franny, Runcorn**

Krazy Kopter

HOVER above the platform on the right hand side of the screen This will protect you from being shot by the boat below If you are very accurate with your bombs you can get extra points by hitting the missile when it appears – **Nigel Bowley, Hockley, Essex**

Mercenary 2 – The Second City

HERE is a tip for getting into the programmer's special cheat rooms When you start board the Dominion Dart and fly to a height of over 350 metres then level out Press 9 and then keep > pressed until you reach a speed of around 1781 kph

Fire a bullet and as you fly close to it pick it up by pressing T Then fly back to location 08 08 and pick up the object that you started the game inside

At this point fly to any elevator – the one at location 08-01 is probably the easiest one to get to

Go underground and walk to the triangular door You don't get the usual 'locked' reply and you can walk straight in

You now have the key to every door and you can get into any hanger out of prison and amass millions of credits easily It will also be easy to find the Novadrive and the intergalactic starship and escape

Final quick tip In one of the complexes out in the wasteland is a room that is bright white inside If you walk around the room and along the walls after a while you will find the bar chart from the exchequers – **Paul Mylet, Woking, Surrey**



£1.25

The Micro User



£1.25

Electron User



£1.50

Apple User

£1.25

Atari ST User

£1.25

[illegible]



£1.25

Amstrad Computer User

£1.25

[illegible]

£1.25

Amstrad Professional Computing



£1.25

Computing with the Amstrad CPC

£1.25

Computing with the Amstrad PCW

£1.95

PC Amstrad

Something old, something new . . .

NEIL FAWCETT takes a look at Atari's latest baby

IN nice time for Christmas, here's something new from Atari – the XE Games System With its low price it will be at the top of lots of present lists, so let's take a look at how it performs

This month we'll assess the new hardware next month we'll delve deeper and reveal how it compares with the rest of the 8 bit range

The first thing that hit me was the machine's new external design Atari has put a lot of thought into this and it has paid off The XE is very pleasing to the eye

Although there has been little change in the technical specification, both the overall design of the main board and the layout have changed

Atari is selling the XE games console in several forms (see panel on facing page) The three systems range from one that is only suitable for games up to one that can be used for any micro application and will even suit serious programmers

We'll take a look at the individual components so you can best choose which system is for you

The Game console

This is the heart of the system, and a rectangular case houses what I class as the best 8 bit technology on the market There is a serial port on the rear two joystick ports and sockets for cartridge keyboard and mains The DIN audio/video output socket found on earlier machines is replaced by two phono sockets

The parallel bus that featured on all XL micros has gone, and so has the expansion bus that appeared on the 130XE The cartridge socket, power switch Option, Start and Select switches are located on the top of the casing making them easy to access The switches are coloured in pastel shades and add to the micro's overall looks

There's an extra bonus built into the console in the form of the old Atari Missile Command game a classic in its time The console also has a built in diagnostic test routine that will check the ram, rom, audio channels, screen display and keyboard switches

The console comes with 65 536 bytes of ram available to the user and an operating system of around 28k Contained within the OS is Basic, the game and a self test routine – not bad for a so-called games machine

Keyboard

A standard qwerty keyboard is supplied with the control graphics printed on the front of the keys as with the 130XE – this is designed to save you time constantly referring to manuals

The keyboard has a lovely feel to it and I found typing at speed very easy Included is a Help key usually found with Start and Option on the 8-bit Atari

It is detachable, so you can type in whatever position you find comfortable This adds a very professional feel to the system

If you POKE 756,204 you will be able to get an international character set if you use the control key in conjunction with key entries

XC12 Tape recorder

Atari tape units have with the exception of the very first 410 recorder been badly designed The XC12 is a vast improvement in a variety of ways

The power supply is now taken from the serial lead and most of the unit is of metal construction and so should last longer than the plastic keys and inserts on the older decks

The unit complements the system nicely, and will also match the 130XE When I plugged the tape deck into the back of my disc drive I had trouble loading tapes but when plugged directly into the console it performed perfectly

Light gun

The gun looks as though it has come straight out of a sci-fi movie and so should appeal to kids of all ages On a disc in the reviews package was a shoot-'em up game that uses the gun to plink at bugs on the screen and it worked fine at a fairly long range

At the moment there is doesn't seem to be any commercial software to take advantage of the gun However, it is easy to write your own because it works like a light pen

To get you started here is a short program to demonstrate the techniques used in reading the information sent from the gun to the micro

```
10 POKE 752,1 REM TURN OFF CURSOR
20 X=PEEK(564) Y=PEEK(565) REM READ X
AND Y COORDINATES OF GUN
30 PRINT CHR$(125) PRINT  X  ,X,Y  Y
 REM PRINT VALUES RETURNED
40 IF STICK(0)=15 THEN SOUND 1,64,6,11
 REM MAKE NOISE IF TRIGGER PRESSED
50 IF STICK(0)=14 THEN SOUND 1,0,0,0 R
EM SWITCH OFF NOISE IF NOT PRESSED
60 GOTO 20 REM REPEAT THE PROCESS
```

Joystick

The joystick supplied is a standard Atari design that dates back to VCS days While not being the best unit available it does its job and is fairly sturdy

When the system is powered up you are presented with the instantly recognisable blue screen with the message READY – Atari Basic is built into the console This means that all the listings from *Atari User* will work fine The loading and saving procedures for tape are the same as for the XL/XE micro

The system was fully compatible with all the commercial software packages I tried on it – and these ranged from Mini Office II to International Karate All the electronic add-ons tried also worked on the system, including an 850 Interface box, Epson FX80 and Atari 1025 printers

The system will also support a disc drive – my old 810 and my new 1050 drives worked perfectly when loading games or Dos Atari is bringing out a new disc drive the XF 551 and hopefully its design will match the new console to give a very nice looking system

The console is controlled by a 6502 CPU and has the GTIA custom graphics chip and the POKEY custom sound chip both being custom chips dedicated to the Atari range

When these are combined you have at your fingertips some of the best 8 bit electronics to come off the drawing board in the last decade The computer still has the 6520 PIA chip, and so interfacing techniques are the same

Programmers have available to them a palette of 256 colours and with a minimum of effort all can be displayed at once There are 11 graphics and five text modes on offer

The graphic capabilities are superb and spectacular visual efects can be created using the DLI – Display List Interrupt

The POKEY sound chip allows you to control four channels independently with a frequency control ranging from 06Hz to 800Hz – so any sound effects created are quite stunning

Conclusions

The new design is superb, very sleek and smooth Picture quality via the TV output has been improved, giving a display that has lost the tendency to drift out of sync

Including disc software well over 2000 pieces of software will work on the new systems

- **XE Computer Games Console**
  Includes 65XE, built-in Missile Command and joystick £79 95.
- **XE Computer Games System**
  Includes 65XE keyboard light gun built-in Missile Command and joystick flight Simulator II and Bug Hunt games £119 99
- **Starter Pack**
  Includes computing tutorial, 130XE XC12 cassette centipedes Star Raiders Missile Command and Atari Tennis cartridges £139 95

Heart of the new machine

His appetite whetted by our evaluation next month technical editor André Willey will take a detailed look at the fascinating technology behind the launch of the new machine

He will also assess how it compares with the rest of the 8 bit range and come to his own conclusions as to its future in the market



It's the Atari disco show!

LEN GOLDING shows how to brighten up the festive season

OUR offering for the party season is a programmable mains disco light controller. It can generate strobes, chasers, random flashes, pre-set sequences and many other instant atmosphere effects which cannot be matched by units available in the shops.

You can even set up your own son et-lumière displays, switching from one lighting pattern to the next by a single touch on the keyboard.

Each channel can handle up to six 60 watt coloured reflector bulbs so it's powerful enough for most clubs and school rooms, as well as for any home. And the design uses a special triggering system which eliminates radio interference so you can use it alongside your VHF tuner – unlike some commercial units.

Figure I shows the circuit. It's rather more complex than might at first seem necessary but this is because of the need to protect your micro from stray mains voltages and to minimise RF interference.

If you're into electronics you will probably see how most of it works without much difficulty. IC1 is used as buffer and amplify the tiny currents from the joystick port, making them powerful enough to drive four light emitting diodes in a quad opto-isolator.

Your micro can see only this section of the circuit – so far as it is concerned all the high voltage switching takes place in another universe.

To preserve the isolation we've powered the rest of the circuit from a small mains transformer (T1). This must be a centre tapped type, with 6-0-6 volt output capable of delivering at least 50mA.

The outputs from the opto-isolator are fed to the inputs of a quad latch (IC3). If pins 4 and 13 of this IC are high the input pattern is transferred to the four outputs. Otherwise changes at the input have no effect.

TR1 monitors the mains AC [illegible]

to negative voltage [illegible] 50 times a second, pa[illegible] zero volts on each swing. [illegible] downward cycle reaches [illegible] the collector of TR1 goes h[illegible].

This triggers a monostable [illegible] from IC2a and IC2b. Its output [illegible] high for a few microseconds, e[illegible]ing IC3 and allowing the input pattern to flow through to the outputs. When the monostable output returns to its low state IC3 becomes latched, so the outputs remain in their current pattern until the next zero-volt transition.

The combined action of TR1, IC2 and IC3 ensures that the disco lamps cannot switch on or off unless there is practically no voltage across them. This eliminates power surges and consequent RF interference. It also avoids the need for bulky and expensive suppression chokes and capacitors.

IC4 buffers the output signals from

WARNING!

Once the mains supply is connected to the board, triac heat sinks and several other on-board components will become live and must not be touched!

high, current can flow – when it is low, current is blocked.

Now on to the construction side of the article. The printed circuit board is available as always from RH Design who can also supply a ready built and tested module for you to connect up to the mains and mount in a suitable case.

Those of you who prefer to etch your own PCBs can use the pattern shown in Figure II. All holes are 1mm, [illegible]



[illegible]

than [illegible]

All [illegible] the [illegible] minal [illegible] to [illegible] them is [illegible]



TR1 [illegible] will [illegible] cable.

[illegible]



Figure III Component layout

◄ *From Page 35*

contact with the track

If you're planning to run only three or four lamps on each channel you can dispense with the heat sinks Otherwise, smear a little heat-sink compound on the back of each triac fit it to its heat sink and bolt the whole assembly tightly into place on the PCB

Use 6BA or 3mm bolts inserted from the reverse side otherwise there is a risk that the fixing nut will bridge across two tracks Do not solder the leads until you are satisfied that each triac is fitted correctly and that the heat sink vanes cannot touch each other

Now it's time to test the board, and for this you will need some kind of meter set to measure around 5V Start by inserting IC1 and connecting the joystick lead then plug into port 1 and run Program I Check each of IC1's outputs – pins 6, 3, 8 and 11 – they should all be high (about +5V)

Now type 1 and hit Return Pin 6 should fall low (0V), while the other three outputs remain high The same should occur for pins 3 8 and 11 when you type 2,4 and 8 respectively If these tests work correctly, it means that the first section is fully operational Now you need to power up the rest of the circuit.

The safest way of doing this is to connect a 6V battery to the terminal block, with its positive lead going to one of the points marked 6V, and its negative lead to 0V

Alternatively, wire your transformer to the mains via an external terminal block, and fit the secondaries to the PCB. The specified transformer has three secondary wires Fit the two same coloured ones to the 6V points – it doesn't matter which way round they go – and the different one to 0V

Check that 5v appears at each IC



Figure IV Bulb layout

socket – pins 14 and 7 of IC2, 5 and 12 of IC3 and 14 and 7 of IC4 If not, you have probably inserted the voltage regulator incorrectly, or left out one of the wire links

Insert the opto-isolator and repeat the 1, 2, 4, 8 testing sequence using Program 1, but this time check the inputs at the socket of IC4 (pins 2, 3, 7 and 6) They should go low in sequence

Disconnect the power supply, insert IC3 and IC4, and reconnect the low voltage supply Temporarily link pins 4 and 14 at the socket of IC2 This will unlatch IC3, so that section 3 can be tested

Go through the 1, 2, 4, 8 sequence again, this time checking that the triac gates go high in the order 1, 2, 3, 4 If all is well, insert IC2 and attach a 60W or 100W mains lamp to each of the triac outputs, as shown in Figure III

WARNING!

Remember that potentially lethal mains voltages are involved so great care is needed in construction and testing!

That's all that can be done without connecting the mains, but if everything is satisfactory so far there should be no further problems

It's best to mount the board in some sort of case or enclosure – a cardboard box will do – to reduce the risk of touching live components while you're testing And remember to unplug the unit from the mains before touching the board

If everything has been wired correctly, the mains lamps should light in sequence when you type 1, 2, 4 and 8 You may like to wire a panel neon in parallel with each output, to act as a monitoring device These can be wired to the eight terminal block along with the lamp leads

You will almost certainly want to design your own display, so there's little point in giving constructional details here The prototype batten was made from square section plastic drainpipe which is very cheap and available from many builders merchants or DIY stores

You might prefer to make up a number of smaller battens say with four lamps each, so that they can be distributed around a large room Whatever method you choose, all the lamps for each channel should be

Turn to Page 38 ▶

Program I Basic test program

```
5 REM PROGRAM 1  TEST DISCO LIGHT UNIT
10 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
20 INPUT N
30 POKE 54016,N
40 GOTO 20
```

Get it right! II

```
 5 CAN (S)
10 CRP (Y)
20 PFF (8)
30 S8V (4)
40 KKK (9)
```

Program II Basic strobe program

```
5 REM PROGRAM 2. SINGLE CHANNEL STROBE
10 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
20 POKE 54016,1 REM SWITCH CHANNEL 1 O
N
30 FOR W=1 TO 10 NEXT W REM ON TIME
40 POKE 54016,0 REM SWITCH ALL CHANNEL
S OFF
50 FOR W=1 TO 50 NEXT W REM OFF TIME
60 GOTO 20
```

Get it right! II

```
 5 CAN (S)
10 CRP (Y)
20 1YE (C)
30 MAF (4)
40 YYC (K)
50 NLO (C)
60 KKM (4)
```

Program III Basic chaser program

```
5 REM PROGRAM 3  FOUR-CHANNEL CHASER
10 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
20 RESTORE 70
30 FOR CHAN=1 TO 4
40 READ D POKE 54016,D
50 FOR W=1 TO 100 NEXT W REM SET SPEED
60 NEXT CHAN GOTO 20
70 DATA 1,2,4,8
```

Get it right! II

```
 5 CAN (S)
10 CRP (Y)
20 SYT (C)
30 3CY (U)
40 99P (0)
50 RRD (2)
60 6U4 (E)
70 RKV (N)
```

Program IV Basic random flash with equal intervals program

```
5 REM PROGRAM 4 - FLASHES LIGHTS IN RA
NDOM COMBINATIONS, WITH EQUAL INTERVAL
S BETWEEN CHANGES
10 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
20 SPEED=100 REM Controls the rate of
change (333 is approx 1 second)
30 N=INT(RND(0)*15)+1
40 POKE 54016,N
50 FOR W=0 TO SPEED NEXT W GOTO 30
```

Get it right! II

```
 5 CAN (S)
10 CRP (Y)
20 SAD (F)
30 ACB (K)
40 S0W (S)
50 34H (R)
```

Program V Basic flash with random interval program

```
5 REM Program 5 - FLASHES LIGHTS IN RA
NDOM COMBINATIONS, WITH RANDOM INTERVA
LS BETWEEN CHANGES
10 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
40 N=INT(RND(0)*15)+1 REM Select Rando
m pattern
50 SPEED=INT(RND(0)*200) REM Select ra
ndom delay
60 POKE 54016,N
70 FOR W=0 TO SPEED NEXT W GOTO 40
```

Get it right! II

```
 5 CAN (S)
10 CRP (Y)
40 CEG (P)
50 55Y (7)
60 5HY (F)
70 34L (A)
```

Program VI Basic program to control flash from keyboard

```
10 REM Program 6 - Keyboard controlled
 sequencer. Press + to advance, +
to go back or ESC to start again
20 X=0 REM Load the DATA into Page 6
30 READ D IF D=-1 THEN 60
40 POKE 1536+X,D X=X+1 IF X>255 THEN ?
 "TOO MUCH DATA" END
50 GOTO 30
60 MAX=X-1
70 POKE 54018,56 POKE 54016,255 POKE 5
4018,60 POKE 54016,0
80 GRAPHICS 2
90 X=0
100 N=PEEK(1536+X)
110 POKE 54016,N
120 POSITION 0,2 ? #6,"CONTROL NUMBER
 ",N,
130 POSITION 0,5 ? #6,"SEQUENCE NUMBER
 ",X,
140 IF X=MAX THEN POSITION 0,7 ? #6,"(
LAST ONE)"
150 IF X<MAX THEN POSITION 0,7 ? #6,"
            ":REM 12 SPACES
160 IF PEEK(764)=255 THEN 160
170 IF PEEK(764)=7 THEN X=X+1*(X<MAX)
GOTO 200
180 IF PEEK(764)=6 THEN X=X-1*(X>0) GO
TO 200
190 IF PEEK(764)=28 THEN X=0
200 POKE 764,255 GOTO 100
210 REM Each DATA item represents a pa
rticular combination of channels  Up t
o 255 may be programmed
220 DATA 0,1,5,3,12,7,2,14,4,15,0,-1
```

Get it right! II

```
10 CP1 (T)    90 D49 (8)    160 LDE (N)
20 DKL (E)   100 ODP (G)    170 UA7 (C)
30 FFF (1)   110 5BC (9)    180 K4J (N)
40 RJ6 (V)   120 YPA (7)    190 T55 (5)
50 KKM (2)   130 252 (A)    200 CXD (5)
60 KA0 (6)   140 66K (W)    210 CYT (8)
70 CRY (S)   150 VMX (K)    220 TAU (C)
80 UNS (V)
```

Number in 54016	PORT 1			
	Chan 1	Chan 2	Chan 3	Chan 4
0	OFF	OFF	OFF	OFF
1	ON	OFF	OFF	OFF
2	OFF	ON	OFF	OFF
3	ON	ON	OFF	OFF
4	OFF	OFF	ON	OFF
5	ON	OFF	ON	OFF
6	OFF	ON	ON	OFF
7	ON	ON	ON	OFF
8	OFF	OFF	OFF	ON
9	ON	OFF	OFF	ON
10	OFF	ON	OFF	ON
11	ON	ON	OFF	ON
12	OFF	OFF	ON	ON
13	ON	OFF	ON	ON
14	OFF	ON	ON	ON
15	ON	ON	ON	ON

Table I Output switching

◄ *From Page 37*

wired in parallel, as shown in Figure IV

The lighting effects available are very easily programmed, and we have listed a few ideas to get you started Table I shows the numbers which must be POKEd into address 54016 to switch on any given combination of channels

Program II is a simple strobe, acting on one channel and Program III is a four-channel chaser Program IV flashes lights randomly at a constant rate, while Program V flashes them randomly at random rate Program VI shows how you can generate a pre-programmed pattern sequence

The unit can handle 500 watts per channel so long as the load is switched on and off every couple of seconds, and no more than two channels are on at the same time If the on period is likely to be longer than this, or all channels will be on simultaneously – however briefly – it's best to keep the total power drain to about 300 watts per channel

	PORT 1				PORT 2			
Pin number	1	2	3	4	1	2	3	4
Control Number	1	2	4	8	16	32	64	128

Table II Switch control numbers

PARTS REQUIRED FOR 4-CHANNEL DISCO LIGHTS CONTROLLER

		Maplin Code
R1 R4	820 ohm (4 off)	M820R
R5	100K 1 Watt	C100K
R6	10k	M10K
R7	100K	M100K
R8 R11	4K7 (4 off)	M4K7
R12 R15	620 ohm (4 off)	M620R
C1	470 mfd 25v	FF16S
C2	0 1mfd miniature disc	YR75S
C3	1000 pf (1nf) ceramic	WX68Y
C4	0 01 mfd miniature disc	YR73Q
IC1 IC4	74AC00 (2 off)	UH67X
IC2	74HC02	UB01B
IC3	74LS75	YF32K
D1 D3	1N4004 (3 off)	QL76H
TR1	BC117	QB34M
SCR1 SCR4	C208D Triacs (4 off)	WQ24B
T1	6-0-6v transformer	WB00A
	Quad opto isolator	YY63T
	75L05AWC +5v regulator	QL26Q
	14-pin DIL sockets (3 off)	BL18U
	16 pin DIL sockets (2 off)	BL19V
	Right angle 9 pin D socket	FG25C

		Maplin Code
	8-way PCB block (2 off)	RK38R
	Fuse clips (2 off) *	WH49D
	6 3A anti surge fuse	RA13P
	Vaned heat sink (4 off) *	FL58N
1 pack	6BA x ¼" RH bolts	BF05R
1 pack	6BA nuts	BF18U
	Silicon grease *	HQ00A

All the above components are available from

Maplin Electronic Supplies P O Box 3 Rayleigh
Essex SS6 8LR Tel 0702 552911

The printed circuit board (order code DBP16) at £4 88 and joystick extension lead (order code AT111) at £2 99 are available from

R H Design 137 Stonefall Avenue, Harrogate
North Yorkshire HG2 7NS Tel 0423 508359

* *These components may not be needed – see text*



Keystick

BRUCE WOODLAND provides a utility for a programmable interrupt driven joystick

WHEN you write programs it is often necessary to provide both cursor key and joystick options to widen their user appeal. If the micro could be fooled into interpreting a joystick input as a predesignated keypress the user would have the best of both worlds and you'd have less programming to do.

This utility allows you to ignore joysticks as you write your program, but still make use of them in the final product. To do this first type in the listing, remembering to use Get it Right III and save a copy to disc or tape.

When the routine is run it will set up an interrupt driven machine code program residing in page 6. This new routine will constantly scan joystick port 1 and interpret all joystick movements as key inputs.

It accomplishes this by sampling input from the port, translating it into the required internal key code and writing this information to the keyboard register at regular intervals.

This sampling rate is normally matched to the keyboard auto repeat but if the fire button is pressed the time delay between the sampling is shortened. The routine has two modes of operation and you can toggle between them by pressing Option.

When the program is in memory and running you are presented with a menu of keyboard inputs against joystick movements. At this point you are asked if you wish to accept the values as they are, or to enter new values.

The program will offer you all eight joystick movements and you enter the corresponding keyboard functions. The fire button is always linked to the spacebar.

At this time you are in the first of the two modes and this ties the Control key to all inputs from the joystick, allowing you on screen editing features from the joystick.

To indicate that you are in the editing mode a flashing cursor is present and if the fire button is pressed the cursor will whizz around the screen. The second mode is without the link to Control and you simply get standard keyboard entry.

The machine code routine is not directly relocatable since a definite address must be inserted as a vector and the keyboard addressed by direct indexing methods. This means the routine is disabled by pressing Reset, but it can be re-implemented by

`CALL=USR(1536)`

If you find this utility useful you may wish to modify it as a non resettable AUTORUN.SYS file. The routine could then be stored above Dos and below LOMEM leaving page 6 free for other uses.

```
0 REM
1 REM |*PROGRAMMABLE JOYSTICK*|
2 REM | for cursor editing mode|
3 REM | ..or any 8 key group  |
4 REM |Written by B Woodland,1987|
5 REM |      (c)ATARI USER     |
6 REM
8 REM
10 REM *MAIN PROGRAM*
20 GOSUB 100:REM CODE SETUP
30 GOSUB 400:REM USER PARAMS
40 GOSUB 800:REM ENABLE JOYSTICK
50 REM
89 REM
100 REM *MACHINE CODE SETUP*
110 DIM KCODE(8)
120 ? CHR$(125) ? :? "Please wait    "
130 OPEN #1,4,0,"K" CU=0:A=0:ADD=1536
140 READ DTA
150 IF DTA<1 THEN 180
160 POKE ADD+N,DTA:N=N+1
170 CU=CU+DTA:GOTO 140
180 RESTORE 1100
190 FOR LOOP=0 TO 7:READ DTA
200 KCODE(LOOP)=DTA:NEXT LOOP
270 IF CU=31656 THEN RETURN
280 ? "Data Error    ..Recheck!!!":END
290 REM
400 REM *User Defined Keys*
310 ? CHR$(125):POSITION 13,0
320 ? "KEYSTICK" ? ?
330 ? "Present key assignment. " ?
340 ? "       1  2  3  4  5  6  7  8"
350 ? "Stick Up Dn Lt Rt Lu Ru Ld Rd"
?
360 ? "Keys  ^↑ ^↓ ^← ^→  r  ┬  ├
┤" ?
370 ? "Keys  -  =  +  *  Q  W  A  S";
?
380 POSITION 2,14
390 ? "Change assignment?":GET #1,K
400 IF K=ASC("N") THEN RETURN
```

Turn to Page 40 ▶

◄ From Page 39

```
410 REM Get Users Keycode
420 FOR KEY=0 TO 7:POSITION 2,16
430 PRINT "Key ";KEY+1;:GET #1,K
440 KCODE(KEY)=PEEK(764)
450 POSITION 6+(KEY+1)*3,12
460 ? CHR$(K):NEXT KEY:POSITION 2,16
470 REM Check for Exit Validity
480 RESTORE 1100:LOOP=0
490 READ DTA
500 IF DTA<>KCODE(LOOP) THEN 530
510 LOOP=LOOP+1:IF LOOP<8 THEN 490
520 GOTO 540
530 ? "NOT SUITABLE FOR MODE 1!"
540 ? "OK? (Y/N)";:GET #1,KEY
550 IF KEY<>ASC("Y") THEN 300
560 REM Users Keycodes to RAM
570 A=0:FOR LOOP=0 TO 7
580 POKE ADD+A+LOOP,KCODE(LOOP)
590 NEXT LOOP:RETURN
599 REM
600 REM Enable Joystick Routines
610 CALL=USR(ADD)
620 ? CHR$(125):POSITION 0,10
630 ? "Joystick control now active."
640 RETURN
690 REM
1000 REM Machine Code Data
1010 DATA 104,169,17,141,40,2,169,6,14
1,41,2,169,1,141,26,2,96
1020 DATA 72,138,72,173,31,208,201,3,2
08,13,205,31,208,240,251,173,110
1030 DATA 6,73,128,141,110,6,230,26,2,
173,132,2,208,5,173,110,6
1040 DATA 208,14,169,6,141,26,2,173,13
2,2,208,4,169,21,208,21,162
1050 DATA 7,173,120,2,221,111,6,240,5,
202,16,248,48,9,189,119,6
1060 DATA 77,110,6,141,252,2,189,2,174
,110,6,240,5,189,3,77,203
1070 DATA 2,141,242,2,104,170,104,96,1
20
1080 REM Joystick Codes Table
1090 DATA 14,13,11,7,10,6,9,5
1100 REM Keyboard Codes Table
1110 DATA 14,15,6,7,47,46,63,62
1120 DATA -1
```

Get it right! II

LINE	CHSUM	LINE	CHSUM	LINE	CHSUM
0	CAH (D)	280	6L9 (P)	540	P0T (0)
1	CAJ (1)	290	0YT (Y)	550	SSF (P)
2	CAK (Y)	300	CUU (L)	560	DLW (Y)
3	CAL (O)	310	N61 (I)	570	ELL (5)
4	CAM (R)	320	0H5 (1)	580	X6L (X)
5	CAN (1)	330	TE8 (9)	590	L9U (K)
6	CAP (U)	340	8YF (N)	599	EJW (X)
8	CAR (G)	350	SLM (1)	600	CUX (N)
10	CP1 (H)	360	1F0 (F)	610	05L (0)
20	S2P (L)	370	T6J (H)	620	NL4 (R)
30	SAG (H)	380	YSL (8)	630	FHX (S)
40	SPA (P)	390	NV6 (T)	640	RP4 (M)
50	DCW (N)	400	X55 (L)	690	0YX (S)
60	CP6 (5)	410	CYV (A)	1000	CXN (Y)
100	CUS (2)	420	XMR (P)	1010	W36 (0)
110	WCT (F)	430	T40 (G)	1020	C3N (2)
120	DTW (L)	440	AVH (5)	1030	Y3J (S)
130	TLP (T)	450	SO7 (0)	1040	10F (6)
140	VKS (6)	460	6JE (N)	1050	XWN (F)
150	5K5 (9)	470	0WV (W)	1060	12T (6)
160	0PG (G)	480	J9S (N)	1070	TU0 (H)
170	9WG (A)	490	W8R (9)	1080	DFN (N)
180	XEM (X)	500	UEX (L)	1090	EY1 (L)
190	ULR (0)	510	29N (L)	1100	02M (N)
200	YHS (J)	520	QWC (7)	1110	F06 (W)
270	V9U (8)	530	YV1 (H)	1120	MMX (G)



Green witches and lurking bugs

by Rouloc

PHEW! Never thought I was going to make it in time for this month's issue. There I was in Tarvania (a small village – turn left just past Outer Mongolia and it's first on the right) surrounded by a thousand slavering orcs. I'd have preferred to have thwacked a couple of hundred or so before I took my leave, but time was pressing.

Unfortunately, my transportation spell came out a bit wonky for some reason I still can't fathom. I said Pockstorp at the place in the incantation where I should I should have said Stockport and found myself in an aborigine's hut somewhere in the Australian outback.

Since then my spell has become a little depleted in power so I had to fly back across the world on a broomstick – old-fashioned and undignified but at least it worked.

Still, it's an ill wind and all that. On the way back I stopped off for a quick oil change on the broomstick and bumped into my old friend Brillig from *Atari ST User* – he had just popped into the same garage for a rebore job on his wand.

We got chatting and he happened to mention that he'd found a bug in Infocom's The Lurking Horror and thought my readers might also be interested.

If you have the brass hyrax ring take it into the terminal room where the hacker sits and drop it. Then say "Wear ring" and the program will respond by asking whether you mean the hacker's keyring or the hyrax ring.

If you then indicate that you want the keyring the program tells you that you can't wear it. But examine your inventory and you'll find you've got it – green keys, yale keys and all the rest. Nice bug, even if it's not much use to you.

Hot news from Rainbird – its next Magnetic Scrolls adventure called Jinxter is well under way and should be available soon – it may even be out by the time you read this.

Featuring the same superb graphics and sophisticated parser as The Pawn and Guild of Thieves, Jinxter is a modern and humorous tale set in Aquitania.

The green witches are gaining power in Aquitania thanks to the dispersal of the pieces of a lucky charm bracelet. Your task is to retrieve all seven pieces and link them together to stop the witches taking over.

The interesting thing is that you can't get killed while your luck holds out. Instead, if you have a lethal encounter, you're dumped just past the hazard, thus allowing you to continue further into the adventure. Now that really sounds like good news for all accident prone adventurers.

The mailbag has been groaning ever louder of late and I'm afraid that I've a little catching up to do. Don't despair if you don't get a mention or have to wait a while before your name pops up in this column – I get so many letters it is simply not possible to find room to include all of them.

But rest assured that Ruoloc reads every single one of your missives with great interest and admiration – and very grateful he is, too. The thought of getting back to read the latest batch of letters has more than once spurred me to greater efforts to escape from rat-infested dungeons in foreign climes.

My thanks this month go to Adam

Turn to Page 42 ▶

◀ From Page 41

Marshall of Penrith in Cumbria for his tips on The Price of Magick and Alternate Reality I especially liked one of his tips for the latter – he advises that whenever you get the chance always try to trick giants as they are very thick and very rich!

Paul Clark in Positano was grateful for our map of Worm In Paradise in the August 1987 issue of *Atari User*, but is still having trouble with the Basic listing because using the Eden transport system he keeps getting a Dim error

I thought the program was correct and that the error must be caused by Paul's typing, but is anyone else having the same problem?

I may have got his first name incomplete, but Ty Hays of Nuneaton was not impressed with the same map – but at least it gave him the incentive to get stuck back into the game

He does mention one peculiarity of Worm which I haven t yet had time to check out for myself He says that if you go to the police station type "give me" then "examine all", the program will list out all the items in the game

Ty also wonders what race I come from Well, you ve seen my handsome picture printed on the previous page fairly regularly so you should have no trouble in guessing that I am a dwarf of the magical variety

My feet really are that big – I do a lot of walking on account of my regular faulty recitation of transportation spells – and I have to have all my shoes specially made by the Seven League Boot and Shoe Company

Speaking of small folk, Level 9 has written an adventure about one of my old flames – a young bossy gnome by the name of Ingrid Bottomlow The adventure is called Gnome Ranger and it's a corker – watch these pages for a review

Finally in the hints and tips, I am pleased to be able to help Andrew Blair of Glasgow with Mordon s Quest, Bob Stacy of Cardiff with The Lurking Horror, Peter Goulden of Lincoln with Arrow Of Death Part II Mike Proctor of Shrewsbury with The Pawn and Dean Reynolds of Solihull with Leather Goddesses of Phobos For these and many other readers help is always at hand

I ll try not to get lost next month – I plan to buy a new transportation spell If I do manage to get here without a hitch maybe I ll let you have a list of how all the points in The Pawn are awarded How s that for a treat? Until then, exciting adventuring!

Hints & tips

LEATHER GODDESSES OF PHOBOS

● *Having a tough time in the cage with the gorilla?*

Throw the chocolate into the cage before being strapped down Once in the cage eat the chocolate and you'll be strong enough to pull the bars and get out

● *Sultan's riddle solution eluding you?*

The answer is "riddles"

● *Can't get into the igloo?*

Put the baby in the basket put the basket on the stoop, hide and wait for the baby to be taken into the orphanage

● *Coded message a mystery?*

Replace each letter by its third previous one in the alphabet, for example replace E by B and B by Y Then read the whole message backwards

THE PAWN

● *Five points adrift?*

Don t forget to ask the Devil "What is the wristband for?"

MORDON'S QUEST

● *Cannibal pygmy a problem?*

Make a blowpipe using the bamboo, thorns and berries and kill the pygmy with it.

Now you ve defeated the pygmy you ve got something to feed to the meat eating plant – gruesome stuff!

THE LURKING HORROR

● *Horrible monster keeps flying off with the hand?*

Drive the creature away by throwing the stone at it inside the dome go down to the skyscraper roof and do it again

ARROW OF DEATH Part II

● *Want to go somewhere from the bridge?*

Hold on to the support rope and cut it – then you ll really be swinging! Make sure you've got a soft landing – fluffy leaves?

ATARI USER Classifieds

Has upgrading your computer given you hardware you no longer need? Or have changing interests left you with unwanted software? Then THIS is the place to advertise your surplus items. *Atari User* readers are always on the lookout for a bargain and this is the first place they look!

An added bonus!

Your advert will also be automatically displayed on MicroLink, the electronic mail service operated in association with Telecom Gold This means it will be seen by thousands of computer enthusiasts who can send an instant response

Classified advertisements will be accepted under the following conditions:

- This service is EXCLUSIVELY for the use of private readers No trade ads will be allowed
- To avoid encouraging software piracy, all ads will be carefully vetted before they are accepted
- Ads can only be accepted on this form (or a photocopy of it)
- There is no maximum to the number of words you include in your ad If there is insufficient room on the form continue on a separate sheet of paper
- The cost is 20p per word with a minimum of 10 words
- We GUARANTEE your ad will appear in the January issue (on sale December 23) providing it is received by November 27

- Forty cassettes and twenty discs all originals for sale 1/2 price compatible XL/XE lists Tel 0703 775717
- Atari 800XL year old data recorder plus 15 games £80 Tel 01 840 4217 Mr Hollyoak 7pm
- Atari 800XL, disc drive 1029 printer data recorder lots of software £200 Tel 0708 48477
- Atari 1029 printer plus descender rom £90 duplicating technologies 1050 duplicator board Rev 4 0 £100 Stocksofts disc cracker £10 other original software half price Tel 0424 852284
- Cassettes budget and full priced only £1 or £2 Tel 061 724 4209
- Atari 130XE 800XL 1050 (US Doubler) 1029 joysticks recorder discs cassettes carts, books mags etc £425 o n o Tel 0905 779280 after 6pm
- For sale 130XE 1050 disc drive 850 interface £155 Tel Robin Holland 0308 852428
- Disc drive with Archiver £85 o n o 1029 printer £80 o n o either c/w speech sampler Tel 021 747 3618 evenings
- To sell Gauntlet Summer Games! Trailblaze disc only £8 50 each Also Quickshot Voltmace joysticks £7 each, extension leads 5+ foot £4 75 each Tel 0733 266366
- 800XL for sale £30 Tel Oxford 52270 ask for Hugh
- For sale or trade Silicon Dreams Jewels Darkness Ultima3 Ultima4 Mercenary Compendium Realm Impossibility original discs Mr J Munro 68 Stockbridge Cres Kilbirnie Ayrshire Scotland, KA25 7HE
- Atari 800XL 1050 disc drive 1010 cassette over forty games on disc cassette cartridge, 10 blank discs All dos os joysticks leads hundreds of mags £250 Vectrex for sale as well Tel 01 739 2676
- Atari 130XE XC11 cassette joystick keypad software magazines books £90 Tel 0689 30493
- Wanted 1050 disc drive Tel 0625 28583 evenings
- 800XL 1050 disc drive 1029 printer joystick plus software and books/magazines as new in original packaging £360 o n o Tel 0752 895323 weekends only
- Atari 800XL 1050 disc drive 1010 tape rec discs tapes £200 Tel Dan 0202 896497
- Atari touch tablet and software £19 Write Philip Conibere 21 Durleigh Road Bridgwater Somerset TA6 7HX
- For sale Atari 800XL 1050 disc drive cassette recorder with 150 titles including Ultima IV Trivial Pursuit leaderboard/tournament Autoduel micro league baseball complete quarterback and many more £250 o n o Write or Call Mr A M Norris 10 Molescombe Fairwater Cwmbran, Gwent Tel Cwmbran 86420
- Dragons tail toolkit integrated library 3DS discs £16 Tel 0664 822835
- 130XE 1050 disc drive 1029 printer touch tablet and games Ex condition £280 Tel 0767 51152
- For sale two 800XLs one 1050 disc drive one 1010 recorder three discs four cartridges seventeen cassettes £250 Tel 01 743 6875
- Wanted 1010 recorder working or not Tel Dave (Chertsey) 561469
- Wanted Books ABC s of Atari Atari Roots Also 850 or PR connection Tel Derryck 0923 673719
- Atari 130XE XCII data recorder Quickshot II joystick popular games, cassettes and text books £200 Tel 01 882 4384
- Two Atari 800XL 1050 drive recorder software Mapping the Atari De re Atari other books £220 o n o Tel Huddersfield 0484 533087
- Atari assembler editor make machine code at £15 Tel 0952 841147
- 130XE + mags games utils books 3 joysticks touch tablet + software XCII £275 o n o Tel (0252) 512782
- Original disc adventures for sale prices from £5 Diskey disc utility £7 Star Raiders cartridge £7 Tel 0502 66026
- Software and hardware for sale including Rambo XL ARII Druid etc Tel Lichfield (0543) 252187

Fill in now for the next issue

					10 words £2 00
					15 words £3 00
					20 words £4 00
					25 words £5 00
					30 words £6 00

I certify that any software offered for sale is original and not a copy

Signed__________

Cheque enclosed for £__________

Name__________

Address__________

POST TO Atari User Classifieds Europa House 68 Chester Road Hazel Grove Stockport SK7 5NY



CAPS LOCKS INDICATOR
from Matthew Bernstein

HAVE you ever had problems with the Atari's CAPS key? This five line program provides a cure by giving a visual indication of whether the computer is in uppercase lowercase or control lock

The utility places an extra line of text at the top of the screen which will indicate the state of the CAPS lock mode and this is shown in an abbreviated form on screen

CAPS uppercase
LOWR lowercase
CTRL control lock

The routine is executed by A=USR(1624) and will work in any graphics mode When you change modes the line will be lost so you must re call it again with the USR command

The program contains its own check routine so it will not start the machine code routine if the totals do not match

This prevents the program from crashing the micro if you make a mistake as you type in the program

The machine code sets up a VBI (vertical blank interrupt) which will scan location 702 every fiftieth of a second so the program appears to be working instantly but it only alters the screen display when the keyboard handler registers are changed

```
1 DATA 152,78,7,6,1,0,6,0,0,0,35,33,48
,51,0,44,47,35,43,26,35,33,46,51,0,0,0
,104,162,6,160,30,169,7,32,92,228,96
2 DATA 173,190,2,201,128,208,5,162,6,7
6,61,6,201,64,208,5,162,0,76,61,6,162,
4,160,4,189,76,6,153,10,6,232,136,208
3 DATA 244,76,98,228,51,48,33,35,50,55
,47,44,44,50,52,35,174,48,2,232,232,14
2,5,6,174,49,2,142,6,6,142,0,142,48,2
4 T=0:FOR I=1536 TO 1650:READ D:POKE I
,D:T=T+D:NEXT I:IF T<>8413 THEN ? "DAT
A error, please check again.":END
5 I=USR(1624):DATA 162,6,142,49,2,78,2
7,6
```

Get it right! II

```
1 42L (7)
2 J0S (F)
3 CMC (Y)
4 UM1 (E)
5 YA8 (1)
```

SCROLLING MESSAGE WINDOW
from Eric McGough

HERE is a simple Basic program which you can adapt to suit your own needs It prints a scrolling message in a window on a Graphics 0 screen It is just an example to fire your imagination and you could for example adapt it to print a number which would rise or fall depending on which way the joystick is moved and is then selected as an input when fire is pressed

PROGRAM BREAKDOWN

1 Selects Graphics Mode 0 and dimensions A$ The string is then defined The spaces on either side of the message determine the gap between the blocks of words as they pass through the window B and C are then set to the portion of the string you wish to display which is a chunk of 10 characters starting at the first in the string in this case The line ends with a POKE which switches off the cursor, otherwise it will flash when the message is printed

2 Beginning of the loop to display window The FOR NEXT loop is set to 600 to it keep running until the fire button is pressed and going back to the loop causes a slight blip The window is then positioned where you want it on screen Next the required portion of the message is printed There is also a short loop to slow the scroll

3 Checks to see if the pointer (B C) has come to the end of the string If it has it resets it to the beginning

4 Checks to see if the fire button has been pressed If it has we would then GOTO the desired action, in this case the scrolling will stop

5 Increments B and C so that the message keeps moving to the left and then returns to the beginning of the loop When it has reached 600 it starts again by going to line 2 The loop will keep going until the fire button is pressed

```
1 GRAPHICS 0:DIM A$(39):A$="
  HAPPY CHRISTMAS            ":B=1:C=1
0:POKE 752,1:SETCOLOR 2,0,0
2 FOR A=1 TO 600:POSITION 15,12:? A$(B
,C):FOR W=1 TO 60:NEXT W
3 IF B=29 THEN B=1:C=10
4 IF STRIG(0)=0 THEN END
5 B=B+1:C=C+1:NEXT A:GOTO 2
```

Get it right! II

```
1 65V (O)
2 JKI (A)
3 72E (W)
4 N2W (2)
5 KDE (9)
```

Win £25

IF you've written any useful or interesting five line programs why not send them to us to grace our pages?

We pay £25 for each one published

You should give a full description of the routine and any other details that are relevant And remember if you want your material returning please enclose a suitably stamped package

Simply send a copy of the program on disc or tape together with the documentation – preferably as a word processed file – to

Atari User Europa House 68 Chester Road
Hazel Grove, Stockport,
SK7 5NY

JET BIKE
from Daniel Welch

THIS is a version of the Light Cycle sequence in the Tron film The rules of the game are as for the film If you crash your cycle in to your opponent s trail you will die and the same applies if you crash into the electrified walls that enclose the playfield

The most remarkable thing about the game is the fact that you have a computer opponent racing against you – and all this is achieved in five lines

The program uses data statements to control the movement of the computer and uses Boolean statements to control movement of the player with the joystick The advantage of using these statements are that they are fast and do not take up much space in the program

VARIABLES

P, Q	Position of computer
DP DQ	Directions of computer
R	Locate value of computer
X, Y	Position of player
DX DY	Direction of player
Z	Locate value of player
S	Stick(0) value

```
1 P=1 Q=19 X=78 Y=19 DX -1 DY=0 GRAPHI
CS 21 COLOR 1 PLOT 0,0 DRAWTO 79,0 DRA
WTO 79,39 DRAWTO 0,39 DRAWTO 0,0
2 READ DP,DQ IF DP=0 AND DQ=0 THEN RES
TORE  GOTO 1 DATA 0,1,1,0,0,-1,-1,0,0,
0
3 SOUND 0,200,12,2 LOCATE P+DP,Q+DQ,R
IF R<>0 THEN 2
4 S STICK(0) IF S<>15 THEN DX=(S=5 OR
S=6 OR S=7)-(S=9 OR S=10 OR S=11) DY=(
S=13)-(S=14)
5 LOCATE X+DX,Y+DY,Z IF Z=0 THEN RESTO
RE  X=X+DX Y=Y+DY P=P+DP Q=Q+DQ COLOR
2 PLOT X,Y COLOR 3 PLOT P,Q GOTO 3
```

Get it right! II

```
1 GYR (5)
2 CJS (1)
3 4D2 (E)
4 NYD (S)
5 PWT (4)
```

CHRISTMAS MESSAGE
from Gary Cheung

THIS five liner is a simple program to demonstrate the graphics capabilities of Atari computers and it also sends a seasonal greeting The program draws a Christmas tree with lights and flashes them on and off

PROGRAM BREAKDOWN

10 Sets up graphics Mode 7, sets up colours for the background and the tree Makes the cursor invisible and sets the left margin The dummy PRINT statement enables the new left margin value to come into effect straight away when the message is printed in line 40 This combination enables the message in line 40 to be positioned without the POSITION command and thus reduces the length of the line

20 Draws the Christmas tree

30 Draws the tree lights using the colour in colour register 709

40 Prints the Christmas message in the text window

50 The tree lights are made to flash by changing the value of the colour register 709 This register also affects the message and the text flashes with the lights Poking 709 with 56 gives a dull red and 15 gives a bright white

```
10 GRAPHICS 7 POKE 708,196 POKE 712,18
 POKE 710,0 POKE 752,1 POKE 82,9 ?  X=
80
20 COLOR 1 FOR Y=10 TO 50 STEP 10 FOR
I=X-Y/2 TO X+Y/2 PLOT X,Y DRAWTO I,Y+2
0 NEXT I NEXT Y
30 COLOR 2 FOR Y=10 TO 50 STEP 10 FOR
I=X-Y/2 TO X+Y/2 STEP 2 PLOT I,Y+20 DR
AWTO I,Y+21 NEXT I NEXT Y
40 PLOT X,9 DRAWTO X,11 PLOT X-1,10 DR
AWTO X+1,10 ? "**  MERRY CHRISTMAS  **
 * !*     from ATARI USER
50 POKE 709,56 FOR I=1 TO 300 NEXT I P
OKE 709,15 FOR I=1 TO 100 NEXT I GOTO
50
```

Get it right! II

```
10 FAR (M)
20 PST (V)
30 CAD (Y)
40 DYT (Y)
50 WEO (9)
```



Two discs crammed with the most popular programs from your favourite magazine!

These two exciting compilations bring together some of the very best listings from the pages of *Atari User*.

Whether you like games or prefer more serious pursuits there's something here for you – and you can also learn a great deal from examining and modifying the Basic listings.

Ten of the Best Games

Chopper Rescue – Take command of a helicopter to rescue lost soldiers

Dan Bells – Rescue Esmerelda by negotiating the dangerous obstacles

Spacemaze – Fly your spacecraft through the deadly caverns below the lunar surface

Maxemunch – Guide your munch monster around the maze avoiding its deadly inhabitants

Moneybags – Gobble up all the money but beware of the sinister spiders

Frank the Fruit Fiend – Help Frank eat his favourite food in this platform game

Duck Dash – Dash round and chase up all the ducks before the storm hits the farm

Frogjump – Direct the frog across the busy road in this classic arcade game

Doctor Boris – Help the doctor build the new hospital but watch out for mad Norman

PLUS the latest Get it Right! program to help you correctly type in listings in Atari User

Bounder was the game you liked best of all. Now, in BOUNDER PLUS, we've made it even better – with SIX exciting new screens to test your dexterity. Bounce up and down on the springy trampoline to hit the many targets while avoiding the balloons. (XL and XE only.)

Ten of the Best Utilities

DiscError – Make sense of those Basic error numbers by turning them into words

DiscEdit – Modify those hidden sectors with this superb utility

DiscView – Take a look at all the useful information stored on your discs

Dump 15 – Make prints of your favourite pictures on your Epson or Atari 1029 printer

ArtShow – Load your AtariArtist pictures and create your own fantastic artshow

AutoDirectory – Gain instant access to disc directories without going to Dos

DiscRenumber – Renumber your Basic listings with this useful Autoboot program

Fullprint – Print out any resident character set in full to an Epson printer

DataEditor – Manipulate data with ease whether on disc, cassette or in memory

80 Column – Generate a very impressive 80 column text display on your screen

PLUS the latest Get it Right! program to help you correctly type in listings in Atari User

Frank the Fruit Fiend

Spacemaze

ONLY £4.95 each

. . . or just £1.95 each when you take out a new subscription to Atari User – or if you renew your existing subscription.

TO ORDER PLEASE USE THE FORM ON PAGE 51

Basic route to colourful triangles

I AM starting to learn Atari Basic and have written a program to draw and fill triangles in different colours But I have come across a problem

After drawing a red, orange, blue and green triangle in Graphics Mode 7 I found that when I tried to use different colours they didn t work Can you explain why this is? – **James Cox, Mowbray Leicestershire Age 11**

● Depending on the graphics mode you choose to work in, you are restricted to the allowed number of colours – this is usually proportionate to the resolution of the mode

For example in Graphics Mode 7 you have a screen resolution of 160 by 96 in four colours on a full screen

But in Mode 11 you have a resolution of 80 by 192 pixels in 16 colours, and this will take up roughly 8k of memory before you start But a Mode 7 display will only take up around 4k

When deciding what colour you wish a pixel to be on screen you must first know the limitations of the mode you are working in

It is also possible to alter the screen display by using the SETCOLOR command This will change depending on what mode you are using and full details can be found in any Atari Basic manual

Here are the effects created on a Graphics Mode 0 text screen

SETCOLOR 1,A,B *will alter the intensity of characters on screen*
SETCOLOR 2,A B *will alter the screen colour*
SETCOLOR 4,A,B *will alter the border colour*

A is the colour you want, and can be a number from 0 to 15 B is the brightness or luminance of the colour and is an even number from 0 to 14

So by playing around with the COLOR and SETCOLOR commands you can produce various patterns and shades

WIN A TENNER!

STARTING next month we will award £10 prizes for the most interesting letters sent to us

So now there's more reason than ever to contribute to our lively mailbag pages

Get your pens out, start writing and you could be one of the winners The address

Mailbag Editor
Atari User
Europa House
68 Chester Road
Hazel Grove
Stockport SK7 5NY

Looping into trouble

I WAS playing around with my Atari 400 and wrote this simple program

```
10 FOR F=1 TO 255
20 PRINT CHR$(F),
30 PRINT F
40 FOR W=1 TO 200:NEXT W
50 NEXT F
```

When I ran it the computer seemed to go haywire and refused to do what it was supposed to do Is my computer broken? And if not can you explain what exactly is happening? – **G Abott Glenrothes Fife**

● Firstly your computer is not broken The answer is very simple As the program goes through its loop and prints CHR$(F) to screen it is encountering Ascii control codes

These codes will cause various different things to happen as shown in the table below As you can see, the control codes are scattered throughout the loop that you defined and the best way for you to view them is individually

Ascii code	Effect
27	Escape
32	Blank space
125	Clear screen
155	EOL or Return
253	Keyboard beep

If you add 128 to the Ascii of a character it will appear in inverse video For example ?CHR$(65) will give you A but if you add 128 then give ?CHR$(193) you will get an inverse capital A

Packing in a word processor

IN my first few computer lessons on a BBC Micro I noticed there is a built-in word processor Is it possible for me to fit one to my Atari 800XL in the same way? – **A Faulkner, Barnstaple, North Devon**

● The BBC Micro has space inside for several roms These work in a similar way to cartridges on your Atari, but you can have more than one present at once So a cartridge based word processor such as AtariWriter is the equivalent of a built in one

Getting it right

IN the November 1987 issue of Atari User you published Get it Right III Are the checksums that you published for the old Get it Right! still compatible with this new super high speed version? – **Brenda Tennyson, Sandbach, Cheshire**

● The new Get it Right creates a different checksum to the old program and so makes the two incompatible We considered keeping the numbers the same, but decided that the advantages that could be gained by a completely new program outweighted the advantages of compatibility

For example a feature that the new program has that the old one didn't is a running cumulative check sum

Tweened cartoon

AFTER typing in the excellent Tweaning program from the November 1987 issue of Atari User I drew a cartoon character and tweened him between

Turn to Page 48 ▶

◄ From Page 47

two positions I then printed out the individual screens of the animation using the OS Controller card screen dump utility

Next I stuck the dumps together in book form and if I flick the pages quickly I have a simple animated cartoon

Thank you for a superb utility – I m sure that with a little patience I could make a full length cartoon using it – **Philip Marston, Armitage, Wadd Soft**

ATARI USER Mailbag

WE welcome letters from readers – about your experiences using the Atari micros about tips you would like to pass on to other users and about what you would like to see in future issues

The address to write to is

Mailbag Editor
Atari User
Europa House
68 Chester Road
Hazel Grove
Stockport SK7 5NY

bed and the [illegible] *waking them* [illegible]

I was told [illegible] *will turn this* [illegible] *Ataris, but* [illegible] *beep was still* [illegible] *you tell me how to get rid of this annoying sound? –* **L J Hawkes, Southend, Essex**

● The beep that comes from from an XL/XE computer is generated through the TV speaker But on an Atari 400 there is a small speaker inside the micro

This can easily be turned off by unplugging the wire from the board altogether or placing a switch between it and the speaker

No trivial pursuit

IN my experience the majority of companies today consider customer relations to be a triviality I am very pleased to say that there is a company that can be bothered to be polite and helpful – Noahsoft

When I bought a product called the PL65 compiler from them I had trouble including library files that contain other library files on to my data disc I contacted the company and they replied with the solution to my problem in a very efficient and helpful way – **Lee Fuller Romford, Essex**

Missing locations

I RECENTLY bought a tape version of International Karate I enjoy sport simulations and I was very keen to play the game

The instructions say that you fly to eight different locations around the world and fight in each but when I started to play I found to my horror that I only have two locations to fight in

Later I went to visit a friend who has a disc drive and I was surprised to find that his version has the eight locations

Why is it that tape owners always seem to lose out on games? – **Mark Haddon Hertford, Hertfordshire**

● The problem with the tape version of International Karate concerns loading time The game constantly loads new location screens which is easy on a disc version but if you were to load a new screen from tape the game would take far too long to complete

Assembler required

BEING new to computing and very willing to learn I was attempting to follow the I/O channels article by André Willey But try as I may, I just keep getting stuck

I don t know how to disable Basic and input the machine code program which you published in the March 1987 issue of Atari User

The article doesn't explain how to do this and so I was wondering if you could answer this for me? – **M Kloss, Tamworth, Staffs**

● To enter any machine code program you need an assembler language such as the Atari Assembler/Editor cartridge or Mac/65 from Optimised System Software These and others are available from several of the advertisers in *Atari User*

Cardsharp cornered

SOME people might have noticed something odd about the Knockout Whist program in the September 1987 issue of Atari User

Apart from the first round the computer always seems to win when random trumps are chosen I checked through the program and spotted where the problem occurred and corrected it with the following changes

```
8010 RET 0 IF CHOO=0 THEN TR=
INT(RND(0)*4)+1 GOTO 8030

8020 GOTO 8040
```

This solves the problem of biased trumps – **Simon Sawyer, Winchester, Hants**

Sound of silence

I OWN an Atari 400 and was wondering how to turn off the noisy beeping sound I get whenever I save or load

I use my computer mostly at night when everyone is in

Nice line in language

I RECENTLY bought Turbo Basic from Stortsoft and was stunned by the quality of the product The package contains the Basic with a compiler and although it doesn t contain all the commands that you get with other Basics say for example Basic XL, it does leave the old Atari Basic language standing

So if you feel like a new language for your Atari I would recommend you try it – **A Griffith, Wimborne, Dorset**

Printing out a document

I HAVE had Mini Office II for four months now and think it s a great package but I do have one small problem with the spreadsheet

When I save data from that module and then try to load it into the word processor to print it out in a document all I get is a mess of characters Am I using the package wrongly? – **Monica Harris, Maidstone, Kent.**

● You re using the package correctly, but I'm sorry to say that the spreadsheet only integrates with the graphics package You could print out the part of the spreadsheet you want and then print the document

Cruel to edge connections

FOR a while now I have been programming using OSS s Mac/65 cartridge to write routines that can be called from Basic

In order to test them I have to remove my Mac cartridge and reboot the system with Basic All this removing and replacing isn t exactly beneficial to the cartridge edge connector

Do you or any of your readers know of an edge connector extension that could be fitted to save wear and tear?

Or better still a device that could be fitted between the cartridge port and the cartridge that would allow me to switch the cartridge out without having to remove it? – **A Crawford Laceby, North Grimsby**

● If you own a 130XE the supra hard disc interface would give you a vertical slot for your cartridge This will reduce wear and tear on the port on the computer

Card for the 65XE

AFTER reading the review for the OS Controller card in the November issue of Atari User I decided to buy one and have it fitted to my 130XE by Computerhouse where I obtained very prompt and professional service

I am about to buy a new 65XE games console to add to my collection of Atari computers and was wondering if the card will plug into it – **Keith Pettison, Middlesbrough, Cleveland**

● The card you bought is designed to work on your 130XE only but Computerhouse is planning to bring one out that will fit inside the 65XE

Doctor Boris diagnosis

I TYPED in the program Doctor Boris from the October 1987 issue of Atari User and checked it very carefully but I still get an Error 8 at line 1020

If I take out this line the program runs, but not correctly Is there an error in this line? – **Michael Cain, Beeston, Nottingham**

● The listing that appeared in the magazine contained no errors The message for Error 8 is

INPUT/READ type mismatch error Attempting to enter a non numeric value for a numeric variable

Check your data statements between lines 1040 and 1510 You will probably find that your mistake is somewhere there

It may well be that you have a letter instead of a number a comma at the end of a line full stop instead of a comma or an extra comma were there shouldn t be one

Pokes for games

IS it possible for you print some pokes for Atari games like those I ve seen for other computers? Or is there something unusual about games on the Atari that makes this impossible? – **Sean Canningh, London**

● With a lot of computers the games are loaded using a Basic loader routine This can often be modified or pokes can be entered first and remain active as the program runs But on the Atari machine code games are loaded using a procedure called Boot

This is done by a combination of the Start Option and Select keys being held down as the computer is switched on This causes the game(s) to be loaded directly into memory so there is no way you can enter a poke Also most games software on the market today require you to switch Basic off which makes it very difficult to give you any pokes on the Hints and Tips page

Helpful review

I OWN a Panasonic KPX 1081 printer and was very interested in the review you published on this model in the October 1987 issue of Atari User

After reading it I proceeded to experiment with my printer and discovered a lot of interesting features Thank you for a superb review keep them coming – **Mike Barstow, Birchwood, Cheshire**

Amateur radio

THERE must be thousands of amateur radio operators worldwide who like me are also Atari computer fans

But could you tell me if there is a program or interface that will enable me to receive teleprinter signals on my radio and pass them to my 800XL so I can view them on the screen and finally print them out? – **Sid Thompson, Leyland Lancs**

● We don t know of any programs or add on that will do what you want but the Radio Society of Great Britain may be able to tell you of a product to solve your problem Their address is Radio Society of Great Britain, Lambda House Potters Bar, Herts

Adding on to the 800XL

A LOT of computers these days seem to have the expansion capabilities necessary for adding a second processor the most common of which is the Z 80 Is there such an add on for my 800XL? – **Steve Ward, Newcastle Upon Tyne**

● Quite a while ago Atari did mention that it was about to bring out a second processor for the 8 bit computers The package was called the Atari CP/M Module and was an external microprocessor upgrade that would allow CP/M software to be used on all 8-[illegible] Atari computers

This add on plugs into the serial port and offers the following features

- Z 80 microprocessor
- 4 0 MHz processing speed
- 64k ram
- CP/M 2 2 operating system
- 40/80 column video output (switchable)
- Serial input/output port
- Monitor output

Unfo[illegible] released th[illegible] Britain, w[illegible] because it w[illegible] popular on a [illegible] always crying [illegible]

Enter the magical world of Kerovnia!

This fascinating adventure features the most sophisticated parser around You can type complex sentences and interact with the many characters, including some very intelligent animals

This superb package includes a 44-page novel and a cryptic help section

> ❛The program took three man years of programming time to produce – and it shows The Pawn is the stuff from which cults are made❜
>
> *– **Anthony Ginn, Atari User, May 1986***

Guild of Thieves – it's a steal!

Guild of Thieves is the long-awaited follow up to the award-winning adventure, The Pawn

You're back in the fantasy world of Kerovnia, in the role of a novice thief who has applied to become a member of the illustrious Guild To prove your worthiness you must ransack an island of all its treasures

There are 29 beautiful illustrations, a massive vocabulary and a text parser which is claimed to be more sophisticated than the parser in the Infocom adventures

> ❛This is an absorbing, funny and tantalising adventure and guaranteed to be another sure-fire winner for Rainbird❜
>
> *– **Bob Chappell, Atari User, October 1987***

Suitable for	Product	Format	RRP	Special reader offer	YOU SAVE	Offer including subscription	YOU SAVE
Atari 800/130 with 1050 disc drive	The Pawn	Disc	£19 95	£14 95	£5	£24 95	£10
	Guild of Thieves	Disc	£19 95	£14 95	£5	£24 95	£19

TO ORDER, PLEASE USE THE FORM ON PAGE 51

Protect your Atari .



with this luxury dust cover for your Atari XE or XL It s made of clear, water resistant vinyl and bound with strong cotton

Only £3.95

. . . and your Atari Users

A year s supply of Atari User can be kept in this handsome chocolate brown binder

Only £4.95

Secure storage for your discs



The ideal storage medium for your 5 25in discs

The luxury padded PVC boxes are strongly made to protect your valuable discs and can be packed flat when not in use

Box holds up to 60 5.25in discs

£4.95

Disc Storage Box

NEW

Holds up to 60 5 25" discs	£4.95	7058	☐

Dust Cover

£3.95 UK	130XE	7031	☐
£4.95 Europe/Overseas	800XL	7060	☐

Atari User Binder

£4 95 UK, £5 95 Europe £11 95 Overseas Airmail	7029	☐

Send to: *Database Publications* FREEPOST, Europa House
68 Chester Road Hazel Grove Stockport SK7 5NY

(No stamp needed if posted in UK) *Please allow 28 days for delivery*

Order at any time of the day or night

Telephone Orders	Orders by Prestel	MicroLink/Telecom Gold
061-429 7931	Key *89 then 614568383	72:MAG001

Don't forget to give your name address and credit card number

ENQUIRIES ONLY 061-480 0171 9am-5pm

ORDER FORM

★ Special price if accompanied by subscription or renewal

Valid to 31/12/87

All prices include postage packing and VAT
Overseas orders despatched by Airmail

(✓) £ p

Annual subscription

New

UK £15	7001	☐
Europe (incl Eire) £18	7003	☐
Overseas (Airmail) £33	7004	☐

Commence with ______ issue

Renewal

UK £15	7002	☐
Europe (incl Eire) £18	7701	☐
Overseas (Airmail) £33	7702	☐

Back Issues

£1.50 UK
£2.00 Europe & Eire
£3.95 Overseas

January 1987	7409	☐
February 1987	7410	☐
March 1987	7411	☐
April 1987	7412	☐
May 1987	7413	☐
June 1987	7414	☐
July 1987	7415	☐
August 1987	7416	☐
September 1987	7417	☐
October 1987	7418	☐
November 1987	7419	☐

Mini Office II (see page 28)

Disc 400/800/XL/XE £19.95 7050 ☐
(48k required)
Add £2 for Europe/£5 for Overseas

The Sound Master (see page 61)

NEW

NOT suitable for Atari 400 £14.95 [illegible] ☐
Add £2 for Europe inc Eire/£7 for Overseas

Ten of the Best Games (see page 40)

NEW

Disc ★ [illegible] £4.95 [illegible]014 ☐ ☐
Add £1 Europe inc Eire/Overseas

Ten of the Best Utilities (see page 40)

NEW

Disc ★ [illegible] £4.95 7017/7018 ☐ ☐
Add £1 Europe inc Eire/Overseas

Guild of Thieves (see page 60)

NEW

Atari 800/130 Disc ★ [illegible] £14.95 7019/7020 ☐ ☐

The Pawn (see page 60)

Atari 800/130 Disc ★ [illegible] £14.95 7033/7034 ☐ ☐

Readers in Europe (inc Eire) add £2 Overseas add £4 per item unless otherwise indicated

➡ ➡ ➡ ➡ ➡ TOTAL ______

Payment please indicate method (✓)

☐ Access/Mastercard/Eurocard/Barclaycard/Visa Expiry Date ☐ /

No ☐☐☐☐ ☐☐☐☐ ☐☐☐☐ ☐☐☐☐

☐ Cheque/Eurocheque made payable to Database Publications Ltd.

Name ______ Signed ______

Address ______

Post Code ______

Tel ______

AT12

SOFTWARE Solutions

Your programming problems solved by ANDRÉ WILLEY

I'VE had a tremendously varied set of questions from you this month, starting with a problem from Timothy Herrington from Portsmouth who's having trouble with his memory

❝ *I have been a regular reader of Atari User since 1985 and now have quite a library of your games on disc, together with a menu selection program which runs them I have slightly modified each program so that when I have finished playing the game I can press an exit key to re run the menu program where any of the games can be selected and run*

Generally this works efficiently but if the previous game has used Player/Missile Graphics or machine code routines – which many do – vertical lines of squares are left flickering across the screen These can only be cleared by pressing the System Reset key Sometimes the following game will not run at all, or the screen display is corrupted, and often the only way to cure this is to power off and restart from scratch

Obviously data is being left behind in the memory by the preceding program and this is interfering with the next one For example, if I run Cubes in Space after Chopper Rescue I usually find that once I have completed the first screen of Cubes nothing happens, or only the bottom of the screen moves to the left Is there a routine – it will probably have to be written in machine code to be fast enough – to clear out any left behind data? It is awfully inconvenient to have to re power every time ❞

Well Timothy there are actually a number of problems to be considered to allow you to freely move between Basic game programs Firstly as you have noticed Player/Missile Graphics don't clear themselves properly when you have finished with them

Secondly you might find that some Vertical Blank or Display List Interrupt routines are still running Finally the program might have adjusted some of the OS or Basic work variables – such as the Display List pointer or the top of memory indicator

To clear the PMG data is slightly more complex than just POKEing the enable register to off with the command POKE 559,34 This will stop the ANTIC graphics chip from getting bytes of player data from memory but will leave GTIA – the display generator – free running with random data giving the flickering vertical stripe you have noticed

You can tell GTIA to stop reading new data by using POKE 53277,0 and the stripe becomes solid which is at least some form of improvement GTIA in fact contains a number of temporary registers which hold the incoming PMG data until it can be processed, and since these haven't been specifically zeroed they will still contain the last byte of data received from ANTIC – hence the solid stripe based on that data

The four player registers are located at 53261 53264 ($D00D-$D010), and the single missile register is at 53265 ($D011) These must all be set to zero and while we're doing that we might as well re set the PMG position and size registers at 53248 53260 ($D000 $D00C) and the PRIOR and VDELAY bytes at 53275 ($D01B) and 53276 ($D01C)

Now that we've dealt with the PMGs let's turn off any user defined interrupts which may be running The DLI vector is at 512,513 ($200 $201) and the Immediate and Deferred mode Vertical Blank Interrupts (VBI's) are at 546 547 ($222,$223) and 548,549 ($224,$225) respectively

The normal contents of these registers will depend on the age of your machine and the type of OS it contains The easiest way to find out what number to POKE into them is to use PEEK to find the original value of each location **before** you run any programs at all, and change lines 1120 to 1140 accordingly I've used the standard 130XE values but make sure they are set correctly for your machine or it could be *goodbye program* time.

One point to note here is that you can't just POKE the new values straight in since the OS may want to use any of the vectors at any time, even after you've changed one byte but not the other Thus you should make sure to turn off all interrupts with POKE 54286,0, then POKE the new values into place and only then turn the VBI system back on with POKE 54286 64

Next you should re-set the RAMTOP high memory pointer in case the previous program has tried to reserve space at the top of memory by adjusting it This can be achieved by using POKE 106 160 for a machine with more that 40k of memory Again, you can find out the normal contents by turning the computer off and on again and then using the command PRINT PEEK(106)

Finally just to be sure you should do a GRAPHICS command to set the Display List back to its normal location I'm not saying that these measures will cure every possible problem

```
10 REM CLEAR MEMORY AFTER PROGRAM.
20 REM ADD THESE LINES AT END OF
30 REM OFFENDING PROGRAM
40 REM MAY BE RE-NUMBERED
50 REM ADJUST LINES 1120, 1130,
60 REM 1140 & 1210 ACCORDING TO
70 REM YOUR COMPUTER'S NORMAL
80 REM VALUES FOR THE LOCATIONS
90 REM 1000 REM CLEAN UP PMG REGISTERS
1010 POKE 559,34
1020 FOR BYTE=53275 TO 53277
1030 POKE BYTE,0 1040 NEXT BYTE
1050 FOR BYTE=53248 TO 53265
1060 POKE BYTE,0
1070 NEXT BYTE
1100 REM RESET INTERRUPT VECTORS
1110 POKE 54286,0
1120 POKE 512,206 POKE 513,192
1130 POKE 546,226 POKE 547,192
1140 POKE 548,138 POKE 549,194
1150 POKE 54286,64
1200 REM RESET RAMTOP/DLIST
1210 POKE 106,160
1220 GRAPHICS 0
```

Listing I Memory cleaning routine

Turn to Page 54 ▶

◄ From Page 63

you might encounter – games programmers are a perverse bunch at the best of times. However, Listing I *should* cure most of the common faults and at least give Basic and the OS a fighting chance to do their job correctly.

Merging Basic programs

Now let's move on to another problem. **Mr K R Henwood** from Pembroke Dock, Dyfed writes:

> *I am writing a program in Basic for an 800XL and 1050 disc drive in which I want to interchange different blocks of DATA statements from within the main program – using the ENTER command. For example:*
>
> ```
> 100 ON I GOSUB 500,600,700
> 110 REM REST OF THE PROGRAM
> 500 ENTER "D:DATA1.LST":RETURN
> 600 ENTER "D:DATA2.LST":RETURN
> 700 ENTER "D:DATA3.LST":RETURN
> ```
>
> *This works fine, but when the new segment has been loaded into the computer execution of the program stops and the READY prompt appears. Can the 800XL be re-programmed to continue execution of the main program automatically after the extra lines have been ENTERed from the disc? At the moment I have to restart the program every time with a direct GOTO command in order not to wipe out other data which is stored in arrays.*

There is an answer to your problem and one which may prove useful in solving many other programming difficulties too.

As you have correctly stated, the ENTER command was designed to work in direct mode rather than as a program statement. So it returns control to the editor rather than to the currently resident program. What is needed is a way to control the editor's operation from within a program.

Impossible? No, not really. You need to use a trick often known as 'Return Key Mode' in which you are able to print whatever commands you like onto the screen and have the Basic interpreter execute them just as if you have pressed Return at the end of each line – hence the name.

Listing II is a small program to illustrate the technique, but you could expand it to do much greater things – including allow a program to modify itself directly. Here's how it works.

Lines 10 to 110 set up a string which contains the main portion of the filename. Assuming you use a single number to indicate each separate file then all you need to do is alter that byte within the string – in this case character number 7. Thus line 110 replaces the lowercase X in the string with the number contained in NUMB.

Next comes a GRAPHICS 0 command to avoid corruption from any old lines of text which may still be on the screen. The POKE 559,0 simply turns off the display while the clever stuff goes on – omit it if you want to watch the system in action.

Next lines 130 and 140 print the two instructions which we want to execute in Immediate mode. The two blank PRINTs between each line are to allow for Basic's READY message which will be printed after each immediate mode task is finished.

Since we want to print a quotes symbol and this can't be done from within a string I have used its Ascii value – CHR$(34) – instead. Thus line 130 will print

ENTER "D:DATAx.LST

Once the two lines have been printed the cursor is placed just above the first command to be executed and Return-Key mode is enabled using POKE 842,13. Immediately after this the STOP command temporarily halts the program with the message STOPPED AT LINE 140.

Since Return Key Mode has been set the screen editor won't wait for you to type a command and hit Return – it will instead go straight on to execute the first line it comes to, which will in this case ENTER the new lines for you. Then it will carry on and find the CONT command which will re-start your program.

The line immediately after CONT should always be POKE 842,12 to disable Return Key Mode before you continue with the rest of your program. I've also added a GRAPHICS 0 to turn the screen back on.

This method can be used to do almost anything you want, but it's always best to experiment until you get it just right – some commands such as LIST and the graphics oriented instructions would not be suitable.

```
10 DIM FILE$(20)
20 REM NUMB WILL BE 1,2,3 or 4
30 REM TO INDICATE FILE NUMBER
100 FILE$="D:DATAx.LST"
110 FILE$(7,7)=CHR$(NUMB)
120 GRAPHICS 0:POKE 559,0
130 ? :? :?"ENTER ";CHR$(34);FILE$
140 ? :? :?"CONT"
150 POSITION 0,0
160 POKE 842,13
170 STOP
180 POKE 842,12
190 GRAPHICS 0
200 REM NEW LINES ARE NOW LOADED
```

Listing II: Return-Key Mode demonstration

Before I disappear for another month there's just time to mention a letter I've received from **Chris Simon** from Mold in Clwyd who has just typed in Get It Right III from the November issue of *Atari User*. Not realising that we'd be printing the full source listing this month he went ahead and disassembled it for himself, and found various messages within the code, such as:

```
SELECTION MENU FOR D2
2) INIT DRIVE
3) CHANGE DRIVE #
4) SET NEW OFF
```

He wondered if this is an extra utility provided for more experienced users, and if so how it might work.

Well, sorry to disappoint you Chris, but it's not an extra utility. If you look at the machine code program on Page 57 you will see that there is a 256 byte buffer defined near the end of the listing. As with most other assemblers my own MAC/65 cartridge creates this space by simply skipping the relevant number of bytes, leaving any existing memory contents intact.

In order to configure my 1050 to work correctly with my hard disc and SparteDos I have set up an AUTORUN file which re-programs the system to my requirements at boot time, and it is a portion of this code that inadvertently slipped into the GIR II object file. These bytes could just as easily be zeros, of course, as all they do is pad the boot file out to the required length.

Next time we print the Basic version I'll modify it to skip that area completely and thus save you about 10 lines – although it won't effect the size of the machine code version. Anyway, well spotted Chris. I hope that the listing in this issue will be of interest to you.

Ah well, that's about it for another month. All that remains is for me to wish you all the very best for a great Christmas – and wait for the deluge of mail which will come in from all those new Atari XE games console owners early in the New Year.

Merry Christmas all.

Are you having problems getting your programs to work? Write to Software Solutions, Atari User, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 5NY.

We will answer as many as we can within the pages of Atari User but, unfortunately we cannot give personal replies.

MicroLink
in association with
TELECOM GOLD
NEWSLETTER

Email is good business

BOOKSELLERS Graeme Roberts and Tony Swann who first got in touch through MicroLink's bulletin board are finding electronic mail makes for good business

Graeme made a 12 900 per cent profit on a battered copy of Sowerby's Exotic Minerelogy he sold to Tony a director of natural history specialists Wheldon & Wesley

"I bought the book for £1 from a local junk shop after seeing Wheldon & Wesley's advertisement on the MicroLink BB" said Graeme I thought it was probably worth more than I paid but had no idea I would get as much as £130

Tony Swann was equally delighted with the deal

After a couple of hours hard work with a soft rubber I was able to remove the accumulated dust and grime of 175 years and turn it into a quite reasonable copy which I sold on the phone to a collector in America for £240 the same day he said The three of us are very happy and it's all thanks to MicroLink

The aged scientific tome was a change of theme for Graeme who specialises in out of-print science fiction fantasy and horror and is currently expanding into supplying dealers and collectors in the US His main reason for joining MicroLink is its enormous potential for speeding communications with his clients

Tony also considers MicroLink an extremely useful business tool "It isn't just because of increasing sales and purchases", he says I travel a lot around Britain and Europe and find the Official Airlines Guide saves me much time at the travel agency Telex and the British Rail timetables come in handy too

Overall I'm delighted with the system and it's certainly beginning to pay for itself

Cut the cost of fashion

PEOPLE can now dress themselves from head to toe in the latest fashions with the help of MicroLink

London company Twillfine is using the system to advertise High Street chain store fashion wear at a fraction of normal retail prices

The garments aren't seconds – they're warehouse stock which has to be cleared to make room for new lines

Twillfine's prices are as low as £4 for blouses usually priced £14 99 and £1 50 for shirts which normally retail at more than £13

YOUR chance to join MicroLink – Page 18

New board for chess

MICROLINK subscriber Keith O Connell has challenged the world to a giant electronic game of chess

Playing on the MicroLink bulletin board he says he is willing to take on anyone of average standard

I don't mind how many games I play at once he said Anyone who wants to take part can just mailbox me with their moves in response to my game on the bulletin board

All I ask is that my opponents play for themselves and don't just use a computer chess program to decide their moves I want to play people not a computer – I can do that on my own at home

Micro muscles

MICROLINK subscriber Theo van der Meer has launched a search for software authors with experience of writing for peripherals

He wants them to help him develop a device which allows people with severe muscular problems to use computers

Theo's company, Preston Communications, is UK distributor for a Dutch product that links a muscle or several muscles to a joystick allowing people with all kinds of muscular diseases to control a micro

The device which takes over the five joystick functions, has just completed clinical trials in Holland and is now being tested here

"Our problem is that all the programs to control the device are currently written for the Commodore and we need to have them re written for other machines such as the BBC Micro IBM PC and compatibles Atari, Apricot Apple and Macintosh said Theo We will of course gladly pay for this work"

Tower triumph

TWO years after finding himself out of a job at the age of 56 Yorkshireman Philip Gibbs is boss of his own company and poised for success

With the help of his computer and MicroLink he has launched Sheffield Skyhook to manufacture self erecting towers for closed circuit TV systems

Now his project is nearing completion he is also receiving financial support from British Steel British Coal and the Department of Industry prior to going into full production

Philip has been using MicroLink to improve his communications with the various agencies he deals with and has also found the Kompass Online directory of UK companies invaluable as a source of potential customers

At the moment we are using MicroLink mainly for telex said Philip But when we finally get going full swing we'll be making use of Email as well"

ANDRÉ WILLEY

gives a detailed breakdown of our checksum program

LAST month's Basic program is quite sufficient to generate all the checksums you will ever need, but we are now going to look at the machine code version.

This will allow experienced programmers to tailor it to their own needs, but you should note that you don't need to understand the inner workings of either version in order to use Get it Right III to check your listings.

The program is written in pure machine code, with a simple Basic routine to make to boot tape or disc. So, unlike the original Get It Right!, there's no easy way for you to see what's going on when you use it.

Get It Right III is a fully re-locating piece of machine code – which means that it can place itself anywhere in memory adjusting automatically to take account of its new position. Even its work space is internal, so it won't interfere with anything else you may have loaded, including page 6 space.

If you want to write your own code to interface with ours then you will require a non-relocating version, and that's what we've printed here.

You can specify a new origin address simply enough by changing the ***=$0700** definition on line 140, but once you've assembled it for a given address it must always be loaded there.

Listing I is the assembly code for the cassette version, and contains all the necessary information to make a boot tape.

If you want to make a disc version first type in the listing using an assembler/editor and then enter the extra lines given in Listing II. These will overwrite any cassette specific

PROGRAM BREAKDOWN

180 – 210	Only applicable to the cassette version and contain the six boot header bytes
230	The first line of code to be run – simply jumps to the setup code starting at line 3490
250 – 320	The handler vector table for CIO use – refer to the recent series on I/O Channels for more information
360 – 450	Define the ten internal work bytes used for data storage and condition flags
470 – 690	Perform the CIO Open command. Firstly the buffer pointer and cumulative checksum digit are cleared, then the zero page IOCB is accessed to find the address of the filespec buffer. This should contain either G S or G P and the OUTVEC flag is set accordingly – or if neither is found an error 139 is generated. As with all CIO commands the routine is normally exited by setting the Y register to a value of one and performing an RTS instruction (lines 770 and 780)
710, 730 and 750	Perform the CIO Status, Special and Close functions – all of which simply return with the Y register set to one
800 and 810	Used to return an error 137 if the line length is over 256 characters (the maximum buffer length). Using Basic this should never happen, but it's always best to check for all possibilities
830 and 840	Return an error 146 should the user mistakenly try to GET bytes from the G handler
860 – 930	Contain the Put-byte routine. This dumps the byte into a buffer area, increments the buffer pointer and returns. If the byte is 155 – the End Of Line marker – then the routine jumps to the CALC section of the program which is where the actual checksum is created
950 – 1110	Output a single Ascii character to the screen or printer, depending on the value of OUTVEC. The address of the relevant Put-byte routine within the Operating System is retrieved from the appropriate CIO vector table and this is then pushed onto the stack. The byte to be printed is stored in the A register and the routine is called by executing an RTS. This method works because a JSR instruction places the return address on to the stack in the same way we placed the Put-byte address. When an RTS is found the address to return to is always pulled back off the stack – and so in this case it jumps to our Put-byte routine. This is a cheating way to generate an indirect JSR instruction, which is not included in the standard 6502 instruction set
1150 – 1940	Use this character output routine to print out the checksum line. Firstly the line number is printed – stopping at the first space found – then lines 1430 to 1490 get and print the first digit. lines

lines with the appropriate disc instructions.

Once the disc version is assembled it can be used as an AUTORUN.SYS file, or just a straightforward binary-load if required.

The program breakdown shows how it all works. But remember, the listing printed in last month's *Atari User* is functionally identical to this assembler version, but obviously has some practical differences due to its ability to locate itself anywhere in memory.

This is achieved partly by increased use of relative branch instructions but mainly from the use of a relocation table near the end of the load space. This ensures that any position dependent instructions are modified as they are moved from the load address of $3000 to their new location just above the original LOMEM.

So now you have Get It Right III in two versions – a user version and one that you can modify to suit your own requirements. We'd be very interested to hear your comments on the new system, and of any modifications or additions which you dedicated programmers might come up with.



Figure I Calculating the checksum digits

Listing I Get it Right cassette version

```
10 ;GET IT RIGHT V/2 0
20 ;
30 ;WRITTEN BY ANDRE WILLEY, 1987
40 ;
50 ;N B  NON-RELOCATING CASS VERSION
60 ;
70 HATABS = $031A
80 ZIOCB =  $20
90 EDVEC =  $E400
0100 PRVEC = $E430
0110 EOL =  $9B
0120 SPACE = 32
0130 ;
0140     *=  $0700
0150 ;
0160 ;CASSETTE HEADER BLOCK
0170 ;
0180 START  .BYTE 0
0190      .BYTE [FIN-START+127]/128
0200      .WORD START
0210      .WORD INIT
0220 ;
0230 RUN JMP SETUP
0240 ;
0250 VECTAB ;       HANDLER VECTORS
0260      .WORD OPEN-1
0270      .WORD CLOSE-1
0280     .WORD GET-1
0290      .WORD PUT-1
0300      .WORD STATUS-1
0310     .WORD SPECIAL-1
0320     JMP EXIT
```

Turn to Page 59 ▶

	1600 to 1660 print the second and lines 1670 to 1710 the third. Five bits of data are used for each digit, giving a number between 0 and 31 (see Figure I). This number is then used as an index into the table of valid letters and numbers (lines 3060 and 3070). Note that letters such as I, O and Z are missing to avoid any confusion with the numbers 1, 0 and 2. Finally lines 1740 to 1840 print the cumulative digit surrounded by brackets, and then a Carriage Return. The buffer is then cleared ready for the next line and CIO is exited via an RTS instruction.
1960 – 2990	The part that actually calculates the checksum itself. When a Carriage Return is detected the buffer is scanned, character by character, adding up the coded values for each byte. When the line is completed, or when a rem is encountered, the print out routine starting at line 1150 is called. The process used is quite complicated and is best understood in flow chart form – as shown in Figure II.
3010 and 3020	Contain the text strings for rem and data to allow for testing and setting flags accordingly.
3060 and 3070	Contain the list of valid characters which may be used for the checksum printouts.
3090 – 3420	Provide the initialise code required for correct system reset handling. This includes looking for a blank entry in the OS's handler address table (HATABS) and inserting the address for our own G: driver, then setting MEMLO, LOMEM and APPMHI to tell the system where our code ends. After zeroing the temporary work space the INIT code returns control to the OS, which in turn re-starts Basic.
3440	Defines the 256 byte text buffer used for storing program lines until their checksum has been printed.
3470 – 3700	Executed from the boot loader to set the CASINI (or DOSINI) vector to point to our initialise routine. For disc users they also set up an extra JSR within the INIT code to execute the original DOSINI vector in order to maintain DOS's own pointers. This setup routine does two other things – it prints the 'Loaded OK' message and it sets Basic's Load in Progress flag (location 202) to a value of one. This has the effect of making Basic do a cold start which will reset its pointers with the new LOMEM values to leave space for our code. Since this portion of machine code will only be needed at boot time it is placed outside the LOMEM protected area, which means that it will be erased after it has done its job.

◀ From Page 57

```
0330 ;
0340 ;WORK DATA AREA
0350
0360 CHKS .BYTE 0    ;CUMULATIVE BYTE
0370 CHK1 .BYTE 0    ;CHECKSUM BYTE 1
0380 CHK2 .BYTE 0    ;CHECKSUM BYTE 2
0390 BUFPTR .BYTE 0  ;BUFFER POSITION
0400 DATA  .BYTE 0   ;1=DATA MODE
0410 STRING .BYTE 0  ;1=IN STRING
0420 SHEET .BYTE 0   ;# OF SHEETS
0430 OUTVEC .BYTE 0  ;P OR S
0440 TEMP1 .BYTE 0
0450 TEMP2 .BYTE 0
0460 ;
0470 OPEN LDA #0
0480      STA CHKS
0490      STA BUFPTR
0500      LDY #2      ;TEST P OR S
0510      LDA (ZIOCB+4),Y
0520      CMP #
0530      BNE OP1
0540      INY
0550      LDA (ZIOCB+4),Y
0560 OP1 CMP #EOL
0570      BEQ SET.S
0580      CMP #S
0590      BEQ SET.S
0600      CMP #E
0610      BEQ SET.S
0620      CMP #P      ;SET MODE=P
0630      BNE OPERR
0640      STA OUTVEC
0650      BEQ EXIT
0660 OPERR LDY #139  ;SET DEVICE NAK
0670      RTS
0680 SET.S LDA #S    ;SET MODE S
0690      STA OUTVEC
0700 ;
0710 STATUS
0720 ;
0730 SPECIAL
0740 ;
0750 CLOSE
0760 ;
0770 EXIT LDY #1     ;RETURN (I/O OK)
0780      RTS
0790 ;
0800 OVERRUN LDY #137 ;TRUNCATED REC
0810      RTS
0820 ;
0830 GET LDY #146    ;NO GET FUNCTION
0840      RTS
0850 ;
0860 PUT LDY BUFPTR  ;TRANSFER BYTE
0870      CPY #255    ;OF DATA TO
0880      BEQ OVERRUN ;BUFFER AREA
0890      STA BUFFER,Y
0900      CMP #EOL     END-OF-LINE?
0910      BEQ DO.SUM  ;YES - CALCULATE
0920      INC BUFPTR  ;NO   RETURN
0930      BNE EXIT
0940 ;
0950 CHOUT TAY       ;OUTPUT BYTE
0960      LDX #0
0970      LDA OUTVEC
0980      CMP #P
0990      BEQ PATR
1000 SCAN LDA EDVEC+7 ;GET E: DRIVER
1010      PHA         ;PUTBYTE ADDRESS
1020      LDA EDVEC+6 ;AND EXECUTE IT
1030      PHA
1040      TYA
1050      RTS
1060 PATR LDA PRVEC+7 ;GET P: DRIVER
1070      PHA         ;PUTBYTE ADDRESS
1080      LDA PRVEC+6 ;AND EXECUTE IT
1090      PHA
1100      TYA
```



Figure 8 Flow chart showing the process used for adding a byte to the checksum

```
1110      RTS
1120 ;
1130 DO.SUM JMP CALC
1140 ;
1150 POUT LDY #255   ;PRINT LINE No.
1160 SP  INY
1170      LDA BUFFER,Y
1180      CMP #EOL
1190      BEQ SP1
1200      CMP #SPACE
1210      BNE SP
1220 SP1 CPY #5
1230      BCS P1
1240      STY TEMP1
1250      LDA #SPACE
1260      JSR CHOUT
1270      LDY TEMP1
1280      INY
1290      BNE SP1
1300 P1  LDY #0
1310 P2  STY TEMP1
1320      LDA BUFFER,Y
1330      CMP #SPACE
1340      BEQ P3
1350      CMP #EOL
1360      BEQ P3
1370      JSR CHOUT
1380      LDY TEMP1
1390      INY
1400      BNE P2
1410 P3  LDA #SPACE  ;PRINT SPACE
1420      JSR CHOUT
1430      LDA CHK2    ;GET DIGIT 1 ..
1440      AND #124
1450      LSR A
1460      LSR A
1470      TAY
1480      LDA ASCII,Y
1490      JSR CHOUT   ; ..AND PRINT
1500      LDA CHK2    ;GET DIGIT 2 ..
1510      AND #3
1520      ASL A
1530      ASL A
1540      ASL A
1550      STA TEMP1
1560      LDA CHK1
1570      AND #224
1580      LSR A
1590      LSR A
1600      LSR A
1610      LSR A
1620      LSR A
```

Turn to Page 60 ▶

◀ From Page 59

```
1630      ORA TEMP1
1640      TAY
1650      LDA ASCII,Y
1660      JSR CHOUT   ,   AND PRINT
1670      LDA CHK1     GET DIGIT 3
1680      AND #31
1690      TAY
1700      LDA ASCII,Y
1710      JSR CHOUT   ,   AND PRINT
1720      LDA #SPACE
1730      JSR CHOUT
1740      LDA #(
1750      JSR CHOUT
1760      LDA CHK1    ,GET CUMULATIVE
1770      AND #31     ,DIGIT
1780      TAY
1790      LDA ASCII,Y
1800      JSR CHOUT   ,   AND PRINT
1810      LDA #)
1820      JSR CHOUT
1830      LDA #EOL    ,CARRIAGE RETURN
1840      JSR CHOUT
1850      TYA
1860      PHA
1870      LDA #0      ,CLEAR BUFFER
1880      TAY         ,READY FOR NEXT
1890 WIPE STA BUFFER,Y ,LINE OF DATA
1900      INY
1910      BNE WIPE
1920      PLA
1930      TAY
1940      RTS         ,RETURN TO CIO
1950 ,
1960 CALC LDY #0      ,CLEAR WORK DATA
1970      STY BUFPTR
1980      STY CHK1
1990      STY CHK2
2000      STY SHIFT
2010      STY DATA
2020      STY STRING
2030 ,
2040 MORE LDA BUFFER,Y ,GET CHARACTER
2050      CMP #EOL     END-OF-LINE?
2060      BNE TEST1
2070      JMP POUT
2080 ,
2090 TEST1 TYA        ,IS TEXT REM' ?
2100      PHA
2110      DEY
2120      DEY
2130      DEY
2140      LDA BUFFER,Y
2150      CMP #'
2160      BEQ T1
2170      CMP #SPACE
2180      BNE TEST2
2190 T1   LDX #3
2200 T1A  INY
2210      LDA BUFFER,Y
2220      CMP TEXTR-1,X
2230      BNE TEST2
2240      DEX
2250      BNE T1A
2260      PLA
2270      TAY
2280      LDA STRING
2290      BNE ADD
2300      LDA DATA
2310      BNE ADD     ,NO   ADD VALUE
2320      JMP POUT    ,YES - PRINTOUT
2330 ,
2340 TEST2 PLA        ,INSIDE QUOTES?
2350      TAY
2360      LDA BUFFER,Y
2370      CMP #"
2380      BNE TEST3
2390      LDA DATA
2400      BNE ADD
2410      LDA STRING  ,SET STRING FLAG
2420      EOR #1
2430      AND #1
2440      STA STRING
2450      BNE ADD
2460 ,
2470 TEST3 TYA        ,IS TEXT DATA ?
2480      PHA
2490      DEY
2500      DEY
2510      DEY
2520      DEY
2530      LDA BUFFER,Y
2540      CMP #
2550      BEQ T3
2560      CMP #SPACE
2570      BNE ADD1
2580 T3   LDX #4
2590 T3A  INY
2600      LDA BUFFER,Y
2610      CMP TEXTD-1,X
2620      BNE ADD1
2630      DEX
2640      BNE T3A
2650      LDA STRING
2660      BNE ADD1
2670      LDA #1      ,SET DATA FLAG
2680      STA DATA
2690 ,
2700 ADD1 PLA         ,ADD BYTE TO
2710      TAY         ,CHECKSUM
2720 ADD  LDA #0
2730      STA TEMP2
2740      LDA BUFFER,Y ,GET BYTE
2750      STA TEMP1
2760      LDX SHIFT   ,SHIFT 1-8 BITS
2770      BEQ A3
2780 A1   ASL TEMP1
2790      ROL TEMP2
2800 A2   DEX
2810      BNE A1
2820 A3   LDA CHK1
2830      EOR TEMP2
2840      EOR TEMP1
2850      STA CHK1
2860      LDA CHK1
2870      CLC
2880      ADC TEMP1
2890      STA CHK1
2900      LDA CHK2
2910      ADC TEMP2
2920      STA CHK2
2930 ,
2940 NEXT INY
2950      DEC SHIFT
2960      BPL MORE1
2970      LDA #7
2980      STA SHIFT
2990 MORE1 JMP MORE
3000 ,
3010 TEXTR  BYTE MER ,REM
3020 TEXTD  BYTE ATAD ,DATA
3030 ,
3040 ,PRINT DIGITS FOR CODES 0-31
3050 ,
3060 ASCII  BYTE 0123456789ACDEF
3070        BYTE "GHJKLMNPQRSTUVWXY
3080 ,
3090 INIT LDY #0      ,ADD G  TO TABLE
3100 LOOK LDA HATABS,Y
3110      BEQ FOUND
3120      CMP #G
3130      BEQ SET_MEM ,ALREADY EXISTS
3140      INY
3150      INY
3160      INY
3170      CPY #35
3180      BNE LOOK
3190      JMP SET MEM ,NO SPACE LEFT
3200 ,
3210 FOUND LDA #VECTAB&255 ,ADD ENTRY
3220      STA HATABS+1,Y
3230      LDA #VECTAB/256
3240      STA HATABS+2,Y
3250      LDA #G
3260      STA HATABS,Y
3270 ,
3280 SET MEM LDA #NEW LOMEM&255
3290      STA $02E7   ,SET NEW LOMEM
3300      STA $0E
3310      STA 128
3320      LDA #NEW LOMEM/256
3330      STA $02E8
3340      STA $0F
3350      STA 129
3360
3370      LDX #9      ,ZERO WORK SPACE
3380      LDA #0
3390 IN3 STA CHK1,X
3400      DEX
3410      BPL IN3
3420      RTS
3430 ,
3440 BUFFER  DS 256  ,BUFFER SPACE
3450 NEW LOMEM ,     END OF DRIVER
3460 ,
3470 MESS  BYTE $9D,GET-IT RIGHT-II -
Loaded OK,EOL,EOL,0
3480 ,
3490 SETUP LDA #$3C  ,STOP CASSETTE
3500      STA $D302
3510      LDY #0      ,PRINT LOADED
3520 R1   TYA
3530      PHA
3540      LDA MESS,Y
3550      BEQ R2
3560      JSR CHOUT
3570      PLA
3580      TAY
3590      INY
3600      BNE R1
3610 R2   PLA
3620 ,
3630      LDA #INIT&255 ,SET CASINI
3640      STA $02
3650      LDA #INIT/256
3660      STA $03
3670      INC 202      ,COLDSTART BASIC
3680 ,
3690      CLC          ,NO INIT
3700 FIN RTS
3710       END
```

Listing II Disc modifications for Listing I

```
50 ,N B  NON-RELOCATING DISC VERSION
0140      *=  $2200   ,AFTER DOS RAM
0160 ,
0180 ,
0190 ,AUTORUN SYS FILE, SO NO NEED
0200 ,FOR BOOT SECTOR INFO
0210 ,
3085 INIT
3086 OLD_DOSINI JSR 0 ,(DUMMY VALUE)
3090 IN1 LDY #0       ADD G  TO TABLE
3490 SETUP
3500 ,
3621      LDA $0C     ,STORE ORIGINAL
3622      STA OLD DOSINI+1 ,VALUE FOR
3623      LDA $0D     ,DOSINI INTO OUR
3624      STA OLD DOSINI+2 ,INIT CODE
3625 ,
3630      LDA #INIT&255 ,SET DOSINI
3640      STA $0C
3660      STA $0D
3680      JMP IN1
3690 FIN *=  $02E0
3700      .WORD RUN
```

Shut out the outside world... and lose yourself in a totally new dimension!

NOW you can experience all the fun and excitement of your favourite games without disturbing the rest of the household

The SoundMaster consists of a cleverly designed interface and the very latest high velocity lightweight headphones

- The precision engineered interface is encased in tough plastic with a graded volume control. It connects easily to your micro (leads included) and sits discreetly behind it while in use
- The beautifully constructed stereo headphones are made by leading UK electronics manufacturer Ross. They deliver crystal clear reproduction and are fully guaranteed. They come with a special adapter so you can also use them with your personal stereo or hifi system
- Every Sound Master is supplied in a colourful presentation pack together with detailed instructions to help you get the most from this superb device

PRIORITY ORDER FORM

Please send me the SoundMaster for my

☐ BBC B B+ ☐ BBC Master
☐ Acorn Electron ☐ Amstrad CPC (stereo sound)
☐ Atari 8 bit (excluding Atari 400)

£14 99 (UK) £16 [illegible]

☐ Cheque enclosed payable to Database Electronics
☐ Please debit my Access/Visa no
☐☐☐☐ ☐☐☐☐ ☐☐☐☐ ☐☐☐☐

Expiry date____________________

Signed____________________

Name____________________

Address____________________

Postcode____________________

SEND TO Database Electronics Europe House
68 Chester Road Hazel Grove Stockport SK7 5NY

Order Hotline *061-480 0171*

Orders by Prestel *Key *89 then 614568383*

MicroLink/Telecom Gold *72 MAG001*

ADVERTISERS INDEX

21st Software	22	Meedmore Distribution	26
Acorn	4	MicroLink	16
Centec	58	Miles Better Software	12
Chips	26	Monitor	58
Compumart	29+31	Noahsoft	25
Computer House	40	Page 6	11
Computerware	12	Pathrich	62
Cut Price Software	62	Pyramid	62
Database Electronics	61	Rambit	62
Database Software	20	Red Rat	64
Datel Electronics	25	R H Design	26
Granville	58	Silica Shop	63
J R Davis	52	Software Express	6
Komami	2	Stortsoft	24
Ladbroke Computers	11	STX Software	52
Lightspeed Software	56	Sunaro Software	24

ATARI
LITTLE DEVIL
NIGHT MARES